electric ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 4 POLES 40A, FOR REAR MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM **ENERGY AND AUTOMATION**

| Product designation | | | | Rotary cam |
|---|----------------------------------|----------------------|--|---|
| _ | switches GX40 | | | |
| Product type designation General characteristics | | | | GX40 |
| Switching diagram | | | 69 - Changeover switch without 0 4 poles | |
| N° of elements | | | | 4 |
| Mounting form | | | | O - Rear mounting with black handle |
| Contact characteristics | | | | |
| Rated insulation voltage | e Ui | | | |
| | | IEC/EN | V | 690 |
| | | UL/CSA | V | 600 |
| Rated impulse withstar | | | kV | 6 |
| Conventional free air th | ermal current Ith | | | |
| | | IEC/EN | Α | 40 |
| - | | UL/CSA | Α | 40 |
| Rated operational voltage | | | V | 440 |
| Rated operational impulse voltage | | | kV | 4 |
| Maximum fuse size for | short-circuit protection In (gG) | | | |
| | | 10kA | Α | 40 |
| | | 15kA | A | 35 |
| 5 | | 25kA | Α | 35 |
| Rated short time currer | nt ICW | 4 - | ۸ | 1000 |
| Conductivity | | 1s | Α | 1000 |
| Conductivity | | | | 10/5 mA/V |
| Operational current le l | AC1/AC21A | | | |
| | ACT/ACZTA | | Α | 40 |
| | AC15 | | | 40 |
| | A013 | 110V | Α | 25 |
| | | 220/230V | Α | 22 |
| | | 380/400V | Α | 12 |
| | | 660/690V | Α | 2 |
| Rated operational power | er in AC | | | - |
| | Three-phase AC-3 | | | |
| | · | 220/230V | kW | 7.5 |
| | | 380/440V | kW | 15 |
| | | 500/690V | kW | 15 |
| | Single-phase AC-3 | | | |
| | | 110V | kW | 2.2 |
| | | 220/230V | kW | 4.4 |
| | | 380/440V | kW | 7 |
| | Three-phase AC23A | | | |
| | | 220/230V | kW | 9 |
| | | 380/440V | kW | 18.5 |
| | Circle altera ACCCA | 500/690V | kW | 15 |
| | Single-phase AC23A | 4401 | 1.347 | 0 |
| | | 110V | kW | 3 |
| | | 220/230V 380/440V | kW kW | 5.2 7.5 |
| | | 300/440 V | IV V V | |


electric ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 4 POLES 40A, FOR REAR MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM **ENERGY AND AUTOMATION**

| 48V 60V 10V 20V 40V 24V 48V 60V 20V 24V 48V 60V 10V 20V 40V | A A A A A A A A A W | 40 40 6 0.8 0.25 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 1.6 |
|---|---|---|
| 60V 10V 20V 40V 24V 48V 60V 20V 24V 48V 60V 10V 20V | A A A A A A A W | 40 6 0.8 0.25 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 1.6 |
| 60V 10V 20V 40V 24V 48V 60V 20V 24V 48V 60V 10V 20V | A A A A A A A W | 40 6 0.8 0.25 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 1.6 |
| 10V 20V 40V 24V 48V 60V 20V 24V 48V 60V 10V 20V | A A A A A A A W | 6 0.8 0.25 40 (1) 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 1.6 |
| 24V 48V 60V 10V 20V 24V 48V 60V 10V 20V | A A A A A A A W | 0.8 0.25 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 1.6 |
| 24V 48V 60V 10V 20V 24V 48V 60V 10V 20V | A A A A A A A W | 0.25 40 (1) 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 1.6 |
| 24V 48V 60V 10V 20V 24V 48V 60V 10V | A A A A A A A W | 40 (1) 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 |
| 48V 60V 10V 20V 24V 48V 60V 10V | A A A A A A W | 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 |
| 48V 60V 10V 20V 24V 48V 60V 10V | A A A A A A W | 40 (1) 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 |
| 60V 10V 20V 24V 48V 60V 10V 20V | A A A A A A W | 40 (3) 40 (3) 12 (4) 40 32 16 3 0.5 0.15 |
| 10V 20V 24V 48V 60V 10V 20V | A A A A A W | 40 (3) 12 (4) 40 32 16 3 0.5 0.15 1.6 |
| 24V 48V 60V 10V 20V | A A A A A W | 12 (4) 40 32 16 3 0.5 0.15 1.6 |
| 24V 48V 60V 10V 20V | A A A A W | 40 32 16 3 0.5 0.15 1.6 |
| 48V 60V 10V 20V | A A A A W | 32 16 3 0.5 0.15 1.6 |
| 48V 60V 10V 20V | A A A A W | 32 16 3 0.5 0.15 1.6 |
| 60V 10V 20V | A A A W | 16 3 0.5 0.15 1.6 |
| 10V 20V | A A A W | 3 0.5 0.15 1.6 |
| 20V | A A W | 0.5 0.15 1.6 |
| | A W | 0.15 1.6 M4 |
| +U V | W | 1.6 M4 |
| | | M4 |
| | Nm | |
| | Nm | |
| | INIII | |
| | | 1.2 |
| | | |
| | A1A/O | 4.0 |
| min | AWG | 16 |
| Max | AWG | 8 |
| | 414/0 | 4.0 |
| min | AWG | 16 |
| Max | AWG | 10 |
| | | 4.5 |
| min | mm² | 1.5 |
| Max | mm² | 6 |
| | | 4.5 |
| min | mm² | 1.5 |
| iviax | | 10 |
| | cycles | 1X10 ⁶ |
| | | |
| | | |
| 00) (| ш | _ |
| | | 5 |
| | | 10 |
| | | 15 |
| υυν | HP | 15 |
| | | |
| | | 2 |
| 40V | HP | 5 |
| | | |
| | | |
| | | |
| | °C | -25 |
| min | | +55 |
| 1 | Max 120V 240V 480V 600V 120V 240V | cycles 120V HP 240V HP 180V HP 300V HP 120V HP |

electric ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 4 POLES 40A, FOR REAR MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

ENERGY AND AUTOMATION

| | min | °C | -40 |
|-------------------------|-----|----|------|
| | max | °C | +70 |
| Resistance & Protection | | | |
| Frontal IP degree | | | IP65 |
| Terminals IP degree | | | IP20 |
| Dimensions | | | |
| Wiring diagrams | | | |



Certifications and compliance

Compliance

CSA C22.2 n° 14
IEC/EN/BS 60947-1
IEC/EN/BS 60947-3
IEC/EN/BS 60947-5-1
IEC/EN/BS 61058-1
UL60947-4-1

Certificates

cULus EAC

ETIM classification

ETIM 8.0

EC001029 -Selector switch, complete