

PRODUCT-DETAILS

MS165-42

MS165-42 Manual Motor Starter 30 ... 42 A



Informations générales

Extension du type de produit	MS165-42
Code de produit	1SAM451000R1015
EAN	4013614486098
Description courte	MS165-42 Manual Motor Starter 30 ... 42 A

Description longue

MS165 is a compact and powerful range for motor protection up to 45 kW (400 V) / 80 A in width of 55 mm. They offer a reliable protection for motors in the event of overload or phase failure. The devices have trip class 10.

This type has also a clear and reliable indication of fault in a separate window in the event of short-circuit tripping. Further features are the build-in disconnect function, temperature compensation, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter (also known as motor protection circuit breaker or manual motor protector) is suitable for three- and single phase applications. The handle is lockable to protect against unauthorized changes. Auxiliary contacts, signaling contacts, undervoltage releases, shunt trips, power in-feed blocks are available as accessory. These are suitable throughout the MS116/MS132/MS165 range.

Commande

Quantité minimum	1 pièce
Code douanier	85362010

Downloads Préférés

Fiche produit, informations techniques	2CDC131083D0201
Instructions et manuels	2CDC131081M6801
Instructions et manuels (Partie 2)	2CDC131060M0202
Ex Operating Instructions	2CDC131087M6801
Time-Current Characteristic Curve	1SAM400505F0005
I ² t Characteristic	1SAM400506F0001
Cut-off Current Characteristic	1SAM400507F0001
CAD Dimensional Drawing	2CDC001079B0201
Schéma dimensionnel	1SAM400401F0001

Dimensions

Produit Largeur Net	55 mm
Produit Hauteur Net	142.65 mm
Produit Longueur Net	122.1 mm
Poids net	0.97 kg

Technique

Pouvoir assigné de coupure de service en court-circuit (I _{CS})	(230 V AC) 50 kA (250 V DC) 3 Poles in Series 100 kA (400 V AC) 50 kA (440 V AC) 50 kA (500 V AC) 30 kA (690 V AC) 10 kA
Pouvoir assigné de coupure ultime en court-circuit (I _{CU})	(230 V AC) 50 kA (250 V DC) 100 kA (400 V AC) 50 kA (440 V AC) 50 kA (500 V AC) 30 kA (690 V AC) 10 kA
Courant assigné instantané de réglage de court-circuit (I _I)	630 A
Setting Range	30 ... 42 A
Puissance assignée d'emploi AC-3 (P _e)	(400 V) Three Phase 22 kW
Puissance assignée d'emploi AC-3e (P _e)	(400 V) Three Phase 22 kW
Tension	Circuit principal 690 V AC Circuit principal 250 V DC
Courant nominal de fonctionnement (I _e)	42 A
Courant assignée d'emploi AC-3 (I _e)	42 A
Courant assignée d'	42 A

emploi AC-3e (I_e)

Courant assignée d'emploi DC-5 (I_e)	42 A
--	------

Fréquence assignée (f)	Circuit principal 50 Hz
	Circuit principal 60 Hz

Operating Frequency (f_{sw})	0 ... 415 Hz
----------------------------------	--------------

Tension assignée de tenue aux chocs (U_{imp})	Circuit principal 8 kV
---	------------------------

Tension assignée d'isolement (U_i)	1000 V
--	--------

Power Loss	at Rated Operating Conditions per Pole 2.79 ... 5.47 W
------------	--

Nombre de pôles	3
-----------------	---

Courant thermique conventionnel à l'air libre (I_{th})	Main Circuit 42 A
--	-------------------

Indice de protection	Housing IP20
	Main Circuit Terminals IP10

Degré de pollution	3
--------------------	---

Electrical Durability	25000 cycle
-----------------------	-------------

Durabilité mécanique	50000 cycle
----------------------	-------------

Type de borne	Screw Terminals
---------------	-----------------

Connecting Capacity Main Circuit	Flexible with Ferrule 1/2x 1 ... 35 mm ²
	Flexible with Insulated Ferrule 1/2x 1 ... 35 mm ²
	Flexible 1/2x 1 ... 35 mm ²
	Rigid 1/2x 1 ... 4 mm ²
	Solid 1/2x 1 ... 4 mm ²
Stranded 1/2x 1 ... 50 mm ²	

Couple de serrage	Main Circuit 4 N·m
-------------------	--------------------

Wire Stripping Length	Main Circuit 16 mm
-----------------------	--------------------

Recommended Screw Driver	Pozidriv 2
--------------------------	------------

Type d'encastrement	1 ... 6
---------------------	---------

Montage sur rail DIN	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715
	TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715

Minimum Mounting Distance	Electrical Conductive Board, Horizontal - Up to 1000 V 1.5 mm
	Electrical Conductive Board, Horizontal - Up to 400 V 0 mm
	Electrical Conductive Board, Horizontal - Up to 690 V 1.5 mm
	Electrical Conductive Board, Vertical 75 mm
	Other Device Same Type, Horizontal 0 mm
Other Device Same Type, Vertical 150 mm	

Actuator Type	Rotary Handle
---------------	---------------

Contact Position Indication	ON / OFF / TRIP
-----------------------------	-----------------

Normes et standards	CSA 22.2 No. 14
	IEC/EN 60947-1
	IEC/EN 60947-2
	IEC/EN 60947-4-1
	UL 60947-4-1

Technique UL/CSA

Short-Circuit Current Rating (SCCR)	Manual Self-Protected Combination Controllers (Type E), (480Y / 277 V AC) 65 kA
	Manual Self-Protected Combination Controllers (Type E), (600Y / 347 V AC) 30

	kA
	Any UL Listed Fuses or Circuit-Breakers, Group Installations (480 V AC) 65 kA
	Any UL Listed Fuses or Circuit-Breakers, Group Installations (600 V AC) 30 kA
	Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (480 V AC) 65 kA
	Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (600 V AC) 30 kA
	Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in Group Installations (480Y / 277 V AC) 65 kA
	Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in Group Installations (600Y / 347 V AC) 30 kA
Maximum Operating Voltage UL/CSA	Circuit principal 600 V AC
Puissance nominale UL/CSA	(200 V AC) Three Phase 10 Hp (208 V AC) Three Phase 10 Hp (220 ... 240 V AC) Three Phase 15 Hp (440 ... 480 V AC) Three Phase 30 Hp (550 ... 600 V AC) Three Phase 40 Hp
Full Load Amps Motor Use	(200 V AC) Three Phase 32.2 A (208 V AC) Three Phase 30.8 A (220 ... 240 V AC) Three Phase 42 A (440 ... 480 V AC) Three Phase 40 A (550 ... 600 V AC) Three Phase 41 A
Locked Rotor Amps	(200 V AC) Three Phase 186.3 A (208 V AC) Three Phase 179 A (220 ... 240 V AC) Three Phase 232 A (440 ... 480 V AC) Three Phase 218 A (550 ... 600 V AC) Three Phase 232 A
General Use Rating UL/CSA	(600 V AC) 42 A
Connecting Capacity Main Circuit UL/CSA	Flexible 1/2x 16-0 AWG Stranded 1/2x 16-0 AWG
Tightening Torque UL/CSA	Main Circuit 35 in-lb

Environnement

Température de l'air ambiant	Operation -25 ... +60 °C Operation Compensated -25 ... +60 °C Storage -50 ... +80 °C
Ambient Air Temperature Compensation	Oui
Altitude de fonctionnement maximale autorisée	2000 m
REACH Declaration	1SAA963005-4502
Résistance aux chocs selon CEI 60068-2-27	11 ms Pulse 25g
Resistance to Vibrations acc. to IEC 60068-2-6	mounted on DIN-rail: 4g / 3 ... 150 Hz mounted on mounting plate: 5g / 3 ... 150 Hz 5g / 3 ... 150 Hz
Informations RoHS	1SAA963006-4502
Statut RoHS	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

Certificats et Déclarations (Numéro de document)

Certificat ABS	1SAA963002-0101
Certificat ATEX	1SAA918001-3901
Certificat BV	1SAA963002-0201

CB Certificate	1SAA918002-2002
CQC Certificate	CQC2015010307760141
Cut-off Current Characteristic	1SAM400507F0001
Declaration of Conformity - CCC	2020980307003042
Déclaration de Conformité - CE	1SAD101100-3408
Declaration of Conformity - UKCA	1SAD201100-3408
DNV GL Certificate	1SAA963002-0301
EAC Certificate	1SAA963000-2701
I _{pt} Characteristic	1SAM400506F0001
IECEX Certificate	1SAA918000-4001
KC Certificate	1SAA963001-1501
Certificat LR	1SAA918001-0501
Certificat RMRS	1SAA918000-0704
Certificat UL	E137861-20150206 E345003-20150206

Emballage

Emballage Niveau 1 Unités	box 1 pièce
Emballage Niveau 1 Largeur	64 mm
Emballage Niveau 1 Longueur	177 mm
Emballage Niveau 1 Hauteur	140 mm
Emballage Niveau 1 Poids	1.1 kg
Emballage Niveau 1 EAN	4013614486098
Emballage Niveau 2 Unités	carton 12 pièce
Emballage Niveau 2 Largeur	330 mm
Emballage Niveau 2 Longueur	400 mm
Emballage Niveau 2 Hauteur	320 mm
Emballage Niveau 2 Poids	13 kg
Emballage Niveau 2 EAN	4013614503955

Classifications

Code de classification d'objet	F
ETIM 5	EC000074 - Motor protective circuit-breaker
ETIM 6	EC000074 - disjoncteur/démarrreur de moteur
ETIM 7	EC000074 - Motor protection circuit-breaker
ETIM 8	EC000074 - Motor protection circuit-breaker

eClass	V11.0 : 27370401
UNSPSC	39121521
Code de catégorie granulaire IDEA (IGCC)	4731 >> Manual Starters
E-Number (Finland)	3707288
E-Number (Sweden)	3110055

Accessories

Identifiant	Description	Type	Quantity	Unit Of Measure
1SAM201901R1001	HKF1-11 Auxiliary Contact	HKF1-11	1	piece
1SAM201901R1201	HKF1-11K Auxiliary Contact	HKF1-11K	1	piece
1SAM201901R1002	HKF1-20 Auxiliary Contact	HKF1-20	1	piece
1SAM201901R1202	HKF1-20K Auxiliary Contact	HKF1-20K	1	piece
1SAM201901R1004	HKF1-01 Auxiliary Contact	HKF1-01	1	piece
1SAM201901R1003	HKF1-10 Auxiliary Contact	HKF1-10	1	piece
1SAM201902R1002	HK1-20 Auxiliary Contact	HK1-20	1	piece
1SAM201902R1202	HK1-20K Auxiliary Contact	HK1-20K	1	piece
1SAM201902R1001	HK1-11 Auxiliary Contact	HK1-11	1	piece
1SAM201902R1201	HK1-11K Auxiliary Contact	HK1-11K	1	piece
1SAM201902R1003	HK1-02 Auxiliary Contact	HK1-02	1	piece
1SAM201902R1203	HK1-02K Auxiliary Contact	HK1-02K	1	piece
1SAM201902R1004	HK1-20L Auxiliary Contact	HK1-20L	1	piece
1SAM201902R1204	HK1-20LK Auxiliary Contact	HK1-20LK	1	piece
1SAM201903R1002	SK1-20 Signaling Contact	SK1-20	1	piece
1SAM201903R1202	SK1-20K Signaling Contact	SK1-20K	1	piece
1SAM201903R1005	SK1-20AR Signaling Contact	SK1-20AR	1	piece
1SAM201903R1205	SK1-20ARK Signaling Contact	SK1-20ARK	1	piece
1SAM201903R1001	SK1-11 Signaling Contact	SK1-11	1	piece
1SAM201903R1201	SK1-11K Signaling Contact	SK1-11K	1	piece
1SAM201903R1004	SK1-11AR Signaling Contact	SK1-11AR	1	piece
1SAM201903R1204	SK1-11ARK Signaling Contact	SK1-11ARK	1	piece
1SAM201903R1003	SK1-02 Signaling Contact	SK1-02	1	piece
1SAM201903R1203	SK1-02K Signaling Contact	SK1-02K	1	piece
1SAM201903R1006	SK1-02AR Signaling Contact	SK1-02AR	1	piece
1SAM201903R1206	SK1-02ARK Signaling Contact	SK1-02ARK	1	piece
1SAM301901R1002	CK1-20 Short Circuit Signaling Contact	CK1-20	1	piece
1SAM301901R1001	CK1-11 Short Circuit Signaling Contact	CK1-11	1	piece
1SAM301901R1003	CK1-02 Short Circuit Signaling Contact	CK1-02	1	piece
1SAM201910R1001	AA1-24 Shunt Trip	AA1-24	1	piece
1SAM201910R1002	AA1-110 Shunt Trip	AA1-110	1	piece
1SAM201910R1003	AA1-230 Shunt Trip	AA1-230	1	piece
1SAM201910R1004	AA1-400 Shunt Trip	AA1-400	1	piece
1SAM201904R1010	UA1-20 Undervoltage Release	UA1-20	1	piece
1SAM201904R1001	UA1-24 Undervoltage Release	UA1-24	1	piece

1SAM201904R1002	UA1-48 Undervoltage Release	UA1-48	1	piece
1SAM201904R1003	UA1-60 Undervoltage Release	UA1-60	1	piece
1SAM201904R1004	UA1-110 Undervoltage Release	UA1-110	1	piece
1SAM201904R1008	UA1-208 Undervoltage Release	UA1-208	1	piece
1SAM201904R1005	UA1-230 Undervoltage Release	UA1-230	1	piece
1SAM201904R1006	UA1-400 Undervoltage Release	UA1-400	1	piece
1SAM201904R1007	UA1-415 Undervoltage Release	UA1-415	1	piece
1SAM201904R1009	UA1-575 Undervoltage Release	UA1-575	1	piece
1SAM401923R1003	S2-M3-50 Power Infeed Block	S2-M3-50	1	piece
1SAM401920R1002	PS2-2-0-125 Busbar	PS2-2-0-125	1	piece
1SAM401920R1003	PS2-3-0-125 Busbar	PS2-3-0-125	1	piece
1SAM401920R1004	PS2-4-0-125 Busbar	PS2-4-0-125	1	piece
1SAM401920R1022	PS2-2-2-125 Busbar	PS2-2-2-125	1	piece
1SAM401920R1023	PS2-3-2-125 Busbar	PS2-3-2-125	1	piece
1SAM401920R1024	PS2-4-2-125 Busbar	PS2-4-2-125	1	piece
1SAM401921R1001	BS2-3 Protection Cover	BS2-3	1	piece
1SAM401922R1001	KA165 Terminal Shroud	KA165	1	piece
GJF1101903R0002	SA2 Terminals and Installation Material	SA2	1	piece
1SAM201920R1011	MSHD-LTB Handles	MSHD-LTB	1	piece
1SAM201920R1012	MSHD-LTY Handles	MSHD-LTY	1	piece
1SAM201920R1000	MSH-AR Shaft Alignment Ring	MSH-AR	1	piece
1SAM101923R0002	MSMN Driver	MSMN	1	piece
1SAM101923R0012	MSMNO Driver	MSMNO	1	piece
1SCA101647R1001	OXS6X85 SHAFT	OXS6X85	1	piece
1SCA108043R1001	OXS6X105 SHAFT	OXS6X105	1	piece
1SCA101655R1001	OXS6X130 SHAFT	OXS6X130	1	piece
1SCA101659R1001	OXS6X180 SHAFT	OXS6X180	1	piece

Catégories

Produits basse tension → Disjoncteurs de puissance → Disjoncteurs-moteurs

Produits basse tension → Produits de Contrôle, Protection et sécurité machines → Disjoncteurs-moteurs → Disjoncteurs-moteurs

