

PRODUCT-DETAILS

# BC7-40-00-01

## BC7-40-00-01 Mini Contactor 24 V DC - 4 NO - 0 NC - Screw Terminals



### Informations générales

|                              |   |
|------------------------------|---|
| Extension du type de produit | BC7-40-00-01  |
| Code de produit              | GJL1313201R0001   |
| EAN                          | 4013614188831   |
| Description courte           | BC7-40-00-01 Mini Contactor 24 V DC - 4 NO - 0 NC - Screw Terminals   |
| Description longue           | The BC7-40-00 mini contactor is a compact 4 pole contactor with screw terminals. They are ideally suited for applications where reliability is a must and space is at a premium. Mini contactors are used in residential buildings, commercial buildings and industrial applications for the control of single or three-phase loads up to 5.5 kW (AC-3) and 20 A / 690 V (AC-1) or switching of control signals. Further features are the noiseless and hum-free coil, a switch position indication and the integrated possibility for rail or wall mounting. |

### Commande

|                  |          |
|------------------|----------|
| Quantité minimum | 1 pièce  |
| Code douanier    | 85365080 |

### Downloads Préférés

|  |                 |
|--|-----------------|
| Fiche produit, informations techniques | 1SBC100214C0202 |
| Instructions et manuels                | 2CDC102047M6801 |
| CAD Dimensional Drawing                | 2CDC001079B0201 |

## Dimensions

|                      |          |
|----------------------|----------|
| Produit Largeur Net  | 52.5 mm  |
| Produit Hauteur Net  | 57.5 mm  |
| Produit Longueur Net | 46.7 mm  |
| Poids net            | 0.175 kg |

## Technique

|  |   |
|--|---|
| Nombre de pôles  | 4   |
| Mini Contactor Type  | Mini Contactor  |
| Tension  | Circuit principal 690 V AC<br>Circuit principal 220 V DC  |
| Fréquence assignée (f)                                     | Circuit de commande DC<br>Circuit principal 60 Hz<br>Circuit principal 50 Hz<br>Circuit principal DC  |
| Tension assignée de tenue aux chocs ( $U_{imp}$ )          | Circuit principal 6 kV  |
| Tension assignée d'isolement ( $U_i$ )                     | 690 V<br>acc. to UL/CSA 600 V   |
| Number of Main Contacts NC                                 | 0   |
| Number of Main Contacts NO                                 | 4   |
| Courant assignée d'emploi AC-1 ( $I_e$ )                   | (220 / 240 V) 40 °C 20 A<br>(220 / 240 V) 55 °C 16 A<br>(380 / 440 V) 40 °C 20 A<br>(380 / 440 V) 55 °C 16 A<br>(690 V) 40 °C 6 A<br>(690 V) 55 °C 6 A  |
| Puissance assignée d'emploi AC-3 ( $P_e$ )                 | (230 V) Three Phase 3 kW<br>(400 V) Three Phase 5.5 kW<br>(500 V) Three Phase 5.5 kW<br>(690 V) Three Phase, NO 3 kW  |
| Courant assigné de courte durée admissible ( $I_{cw}$ )    | at 40 °C Ambient Temp, in Free Air, from a Cold State 10 s 96 A   |
| Number of Auxiliary Contacts NC                            | 0   |
| Number of Auxiliary Contacts NO                            | 0   |
| Courant thermique conventionnel à l'air libre ( $I_{th}$ ) | Main Circuit 20 A   |
| Rated Control Circuit Voltage ( $U_c$ )                    | 24 V DC   |
| Plage d'utilisation de la bobine selon                     | (acc. to IEC 60947-4-1) for DC supply 0.85 ... 1.1 x $U_c$ (at $\theta \leq 55$ °C)   |
| Indice de protection                                       | Control Circuit Terminals IP20<br>Main Circuit Terminals IP20   |
| Durabilite mecanique                                       | 10000000 cycle  |
| Maximum Electrical Switching Frequency                     | (AC-1) 300 cycles per hour<br>(AC-3) 600 cycles per hour<br>(DC-1) 600 cycles per hour<br>(DC-3) 600 cycles per hour  |
| Connecting Capacity Main Circuit                           | Flexible with Ferrule 1/2x 1 ... 2.5 mm <sup>2</sup><br>Flexible with Insulated Ferrule 1/2x 1 ... 2.5 mm <sup>2</sup><br>Flexible 1/2x 1 ... 2.5 mm <sup>2</sup><br>Rigid 1/2x 1 ... 4 mm <sup>2</sup> |

|  |   |
|--|---|
| Connecting Capacity<br>Control Circuit | Flexible with Ferrule 1/2x 1 ... 2.5 mm <sup>2</sup><br>Flexible with Insulated Ferrule 1/2x 1 ... 2.5 mm <sup>2</sup><br>Flexible 1/2x 1 ... 2.5 mm <sup>2</sup><br>Rigid 1/2x 1 ... 4 mm <sup>2</sup> |
| Wire Stripping Length                  | Main Circuit 9 mm   |
| Couple de serrage                      | Control Circuit 0.8 ... 1.1 N·m<br>Main Circuit 0.8 ... 1.1 N·m   |
| Recommended Screw<br>Driver            | M3<br>Pozidriv 1  |
| Montage sur rail DIN                   | TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715<br>TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715  |
| Power Loss                             | at Rated Operating Conditions AC-1 per Pole 1.4 W   |
| Normes et standards                    | IEC/EN 60947-1<br>IEC/EN 60947-4-1<br>IEC/EN 60947-5-1<br>UL 60947-1<br>UL 60947-4-1  |

## Technique UL/CSA

|  |  |
|--|--|
| Maximum Operating<br>Voltage UL/CSA        | Circuit principal 600 V AC   |
| Full Load Amps Motor<br>Use                | (115 V AC) Single Phase 13.8 A<br>(200 V AC) Three Phase 7.8 A<br>(220 ... 240 V AC) Three Phase 9.6 A<br>(230 V AC) Single Phase 10 A<br>(440 ... 480 V AC) Three Phase 7.6 A<br>(550 ... 600 V AC) Three Phase 6.1 A |
| Puissance nominale<br>UL/CSA               | (115 V AC) Single Phase 0.75 Hp<br>(200 V AC) Three Phase 2 Hp<br>(220 ... 240 V AC) Three Phase 3 Hp<br>(230 V AC) Single Phase 1.5 Hp<br>(440 ... 480 V AC) Three Phase 5 Hp<br>(550 ... 600 V AC) Three Phase 5 Hp  |
| General Use Rating<br>UL/CSA               | (600 V AC) 16 A  |
| Connecting Capacity Main<br>Circuit UL/CSA | Stranded 1/2x 22-10 AWG  |
| Tightening Torque<br>UL/CSA                | Control Circuit 7 in·lb<br>Main Circuit 7 in·lb  |

## Environnement

|   |  |
|---|--|
| Température de l'air<br>ambiant                     | Operation -25 ... +55 °C<br>Storage -40 ... +80 °C                     |
| Altitude de<br>fonctionnement maximale<br>autorisée | 2000 m   |
| Résistance aux chocs<br>selon CEI 60068-2-27        | 11 ms Pulse 15g  |
| Resistance to Vibrations<br>acc. to IEC 60068-2-6   | 5g / 5 ... 150 Hz  |
| Statut RoHS   | Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019 |

## Certificats et Déclarations (Numéro de document)

|                                    |                     |
|------------------------------------|---------------------|
| Certificat BV                      | 1SAA920000-0204     |
| CB Certificate                     | 1SAA938000-2002     |
| CQC Certificate                    | CQC2003010304064033 |
| Declaration of Conformity<br>- CCC | 2020980304001854    |
| Déclaration de Conformité          | 1SAD101100-3101     |

- CE

|                                     |                  |
|-------------------------------------|------------------|
| Declaration of Conformity<br>- UKCA | 1SAD201100-3101  |
| DNV GL Certificate                  | 1SAA938000-0306  |
| EAC Certificate                     | 1SAA920000-2702  |
| KC Certificate                      | 1SAA938000-1501  |
| Certificat LR                       | 1SAA938000-0504  |
| Certificat RMRS                     | 1SAA938000-0704  |
| Certificat UL                       | E191658-19881208 |

## Emballage

|                                |               |
|--------------------------------|---------------|
| Emballage Niveau 1<br>Unités   | 10 pièce      |
| Emballage Niveau 1<br>Largeur  | 115 mm        |
| Emballage Niveau 1<br>Hauteur  | 54 mm         |
| Emballage Niveau 1<br>Longueur | 280 mm        |
| Emballage Niveau 1 Poids       | 1.82 kg       |
| Emballage Niveau 1 EAN         | 4013614418884 |

## Classifications

|   |   |
|---|---|
| Code de classification<br>d'objet           | Q   |
| ETIM 4                                      | EC000066 - Magnet contactor, AC-switching                                 |
| ETIM 5                                      | EC000066 - Magnet contactor, AC-switching                                 |
| ETIM 6                                      | EC000066 - contacteur de puissance pour commutation de courant alternatif |
| ETIM 7                                      | EC000066 - Power contactor, AC switching                                  |
| ETIM 8                                      | EC000066 - Power contactor, AC switching                                  |
| eClass                                      | V11.0 : 27371003  |
| UNSPSC                                      | 39121529  |
| Code de catégorie<br>granulaire IDÉA (IGCC) | 4763 >> Power contactor, DC switching                                     |

## Accessories

| Identifiant     | Description                | Type     | Quantity | Unit Of Measure |
|-----------------|----------------------------|----------|----------|-----------------|
| GJL1201317R0002 | CA6-11E Auxiliary Contact  | CA6-11E  | 1        | piece           |
| GJL1201317R0003 | CA6-11M Auxiliary Contact  | CA6-11M  | 1        | piece           |
| GJL1201317R0004 | CA6-11N Auxiliary Contact  | CA6-11N  | 1        | piece           |
| GJL1201330R0003 | CAF6-11M Auxiliary Contact | CAF6-11M | 1        | piece           |
| GJL1201330R0006 | CAF6-20E Auxiliary Contact | CAF6-20E | 1        | piece           |
| GJL1201330R0011 | CAF6-02M Auxiliary Contact | CAF6-02M | 1        | piece           |
| GJL1201330R0007 | CAF6-20M Auxiliary Contact | CAF6-20M | 1        | piece           |
| GJL1201330R0012 | CAF6-02N Auxiliary Contact | CAF6-02N | 1        | piece           |
| GJL1201330R0008 | CAF6-20N Auxiliary Contact | CAF6-20N | 1        | piece           |
| GJL1201330R0002 | CAF6-11E Auxiliary Contact | CAF6-11E | 1        | piece           |
| GJL1201330R0004 | CAF6-11N Auxiliary Contact | CAF6-11N | 1        | piece           |
| GJL1201330R0010 | CAF6-02E Auxiliary Contact | CAF6-02E | 1        | piece           |
| GJL1201906R0001 | LT6-B Cover Cap            | LT6-B    | 1        | piece           |
| GJL1201904R0001 | BN6 Plunger                | BN6      | 1        | piece           |

## Catégories

Produits basse tension → Produits de Contrôle, Protection et sécurité machines → Contacteurs → Mini contacteurs

