

AR111 & PAR36 18.5W Transformer Compatibility - ASIA

Mfg	Model	Wattage	Voltage	Class / Frequency	Country	Transformer Type	1 Lamp
Asia							
AcTec	Ultra 70	70	220-240	50	Asia	Electronic	Pass
ATCO	Speedy TED 105	35-105	240	50	Australia	Electronic	Pass
EZ Lighting	SI-H2501SL	48	220	60	Korea	Electronic	Pass
Hytronik	HE4030-A		230	50	EU	Electronic	Pass
(Korean)	HU2501	50	220	50	Korea	Electronic	Pass
Meanwell	LVP-35-12	DC 12V	100-240	50/60	Taiwan	Electronic	Pass
Meanwell	PWM-90-12	90	100-305	50/60	World	Electronic	Pass
Osram	ET Parrot 105	35-70	220	50	Asia	Electronic	Pass
Osram	ET-A 60	60	220-240	50	Singapore	Electronic	Pass
Osram	ET-P 60	20-60	220-240	50	Australia/Thailand	Electronic	NC
Osram	ET-RedBack	60	230-240	50	Australia	Electronic	Pass
Osram	HTM 105	35	240	50	Australia	Electronic	Pass
Osram	HTM 70	20-70	240	50	Australia	Electronic	Pass
Philips	EHC150F		110	50/60	Taiwan	Electronic	Pass
Philips	ET-E 60	20-60	220-240	50	Singapore	Electronic	NC
Philips	ET-S 60	20-60	220-240	50	Thailand	Electronic	Pass
Philips	Primaline 105	35-105	220	50	Asia	Electronic	Pass
Philips	Primaline 70	20-70	220	50	Asia	Electronic	Pass
Racer	RCT 50	60	220	50	Thailand	Magnetic	Pass
Vossloh Schwabe	EST 105	20-105	240	50	Australia	Electronic	Pass

Notes: Compatibility tests are conducted by Soraa only as guidance for the user

All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site

Results may vary due to variability in component choices and manufacturing processes by the dimmer or transformer manufacturer

Above table is for applications where no dimmer is used. If a dimmer is used, the user should consult the Dimmer/Transformer table, or contact Soraa if their desired combination is not listed.

	Pass
NC	Not compatible
Blank cell	Not tested