



LED High Intensity Lamps

Our high intensity LED lamps are an easy, cost saving retrofit solution that can replace up to 250 W HID lamps. With different colour temperatures, wattages and base options, they are the perfect replace HID lamps. These LED retrofits are ideal for many applications such as churches, area lighting and industrial lighting.

No need for a time consuming fixture replacement, simply bypass the ballast and screw the lamp in. The ballast bypass is the best option for long term installations since it prevents the need to go back and replace the ballast at a later time, making it ideal for hard to reach spaces.



Order Code	Description	Watts (W)	Base	Volts (VAC)	Colour temp. (K)	CRI	Life L70 (hrs)	Lumen output (lm)	Operating position	Case qty (master)
65042 ¹	LED/CRN/22W/30K/ND/BYP/120-277/STD	22	E26	120-277	3 000	84	50 000	2 309	Universal	24
65043 ¹	LED/CRN/22W/40K/ND/BYP/120-277/STD	22	E26	120-277	4 000	84	50 000	2 674	Universal	24
65044 ¹	LED/CRN/22W/50K/ND/BYP/120-277/STD	22	E26	120-277	5 000	83	50 000	2 681	Universal	24
65045 ¹	LED/CRN/36W/30K/ND/BYP/120-277/STD	36	E26	120-277	3 000	84	50 000	4 016	Vertical	12
66003 ¹	LED/CRN/36W/40K/ND/BYP/120-277/STD	36	E26	120-277	4 000	84	50 000	4 414	Vertical	12
65046 ¹	LED/CRN/36W/50K/ND/BYP/120-277/STD	36	E26	120-277	5 000	83	50 000	4 495	Vertical	12
65048	LED/CRN/54W/40K/ND/BYP/E39/120-277/STD	54	E39	120-277	4 000	80	50 000	7 020	Universal	12
66004	LED/CRN/54W/50K/ND/BYP/E39/120-277/STD	54	E39	120-277	5 000	82	50 000	6 855	Universal	12
65047 ²	LED/CRN/120W/40K/ND/BYP/E39/120-277/STD	120	E39	120-277	4 000	84	50 000	14 570	Vertical	4
66005 ²	LED/CRN/120W/50K/ND/BYP/E39/120-277/STD	120	E39	120-277	5 000	83	50 000	15 020	Vertical	4

Accessories

Order Code	Description
10985	Mogul to Medium socket adaptor
10587	Mogul to Mogul socket extension

Traditional Equivalent

LED	CFL	Incandescent	HID
22 W	32 W - 40 W	150 W - 200 W	50 W - 75 W
36 W	55 W - 65 W	300 W	100 W - 150 W
54 W	85 W - 105 W	500 W	150 W - 200 W
120 W	-	-	250 W

Lumen values are derived from photometric testing.
For a complete list of compatible ballasts and DLC qualified products,
please visit www.standardpro.com

¹ Not DLC

² A safety cable is included with this lamp to secure its installation in the fixture.
Make sure to use this cable when installing the lamp to prevent the lamp from falling down.
³ These products comply with UL1598C Standard for LED luminaire Retrofit kits

