

Power Rating and Volt-Ampere Loss for Yokogawa Wattmeters

Power Rating and Volt-Ampere Loss.

Range		Rating		Approx. Internal Impedance	Approx. Volt-Ampere Loss	Code
Voltage Range	Current Range	120 V	240 V			
				6,000 Ω	2.4 VA	
				12,000 Ω	4.8 VA	
0.2/1 A	0.2 A 1 A	4.8 W 24 W	9.6 W 48 W	31.3 Ω 1.09 Ω	1.25 VA 1.09 VA	204111
1/5 A	1 A 5 A	24 W 120 W	48 W 240 W	1.70 Ω 0.06 Ω	1.70 VA 1.50 VA	204112
5/25 A	5 A 25 A	120 W 600 W	240 W 1.2 kW	0.105 Ω 0.004 Ω	2.62 VA 2.50 VA	204113