

SORAA

Electrical compatibility – PAR20 11W 230V lamps - International

Table of contents

- General compatibility guidelines.....Page 2
- Dimming compatibility.....Page 3-5

General compatibility guidelines

Scope

This document provides the basic guidelines regards electrical compatibility of SORAA 230V PAR20 11W lamps and compatibility tables.

Dimmer Compatibility

SORAA 230V PAR20 lamps are made to work with trailing edge (reverse phase) and leading edge (forward phase) phase cut dimmers. However, the use of trailing edge dimmers is preferred and will show in general better behavior .

Dimmer compatibility tables are on pages 3-5.

The percentages for each dimmer combination are the percentage of light output that we were able to dim down to without seeing any problems like flicker/shimmer. Anything 30% or above is considered not compatible and you will see a "NC" in a grey cell.

There might be a minimum wattage load on the dimmer. If this minimum load is not met, there might be compatibility issues.

Maximum number of lamps on a dimmer

The following need to be considered when determining the amount of lamps on a dimmer.

1. SORAA tests have been carried out with 1 lamp unless stated otherwise.
2. There is a repetitive, very brief current spike the LED lamp will see twice per cycle. This current spike has to be provided by the dimmer, and will affect the recommended lamp load on each dimmer.
3. Ultimately the dimmer manufacturer is the only one with authority to rate their product, but SORAA can give an Engineering estimate.
4. We recommend to use a 5.0 de-rating factor for incandescent/halogen dimmers loaded with our 230V lamps.

For example for a 500W dimmer it would mean $500/5 = 100W$ of LED, so an estimated maximum of 9 lamps 11W.

Disclaimer

Compatibility tests are conducted by Soraa only as guidance for the user.

All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site.

Results may vary due to variability in component choices and manufacturing processes by the transformer and dimmer manufacturers.

For more information on the dimmers/transformers, please find specs on the manufacturer's website.

SORAA PAR20 230V 11W - DIMMER COMPATIBILITY LIST - International

Manufacturer	Model	MD #	Edge Trigger	1 lamp Dim (%)	2 lamps Dim (%)	3 lamps Dim (%)	Comments
Arditi		800680	T	0%			Tested by dimmer manufacturer
Aurora		AU-DSP400X	L	17%	13%	21%	
Aurora		AU-DSP651	L	18%	19%	15%	
Berker		2830 10	L	NC	NC	NC	
Berker		286710	T	16%	14%	14%	
Bticino		NT4411N	T	18%	18%	18%	
Busch		2247	L	16%	16%	16%	
Busch		2250 U # 01	L	10%	10%	10%	
Busch		6513	T	NC	23%	21%	
Busch		6523	L	15%	12%	11%	
CABAC		HNS630DT	T	9%	9%	9%	(*)
Clipsal		32E450UDM	T	17%	17%	17%	(*)
Diginet		DGLCDM400	T	10%	10%	9%	
Feller		40.600RL	L	12%	13%	13%	
Feller		40300.RC	T	12%	9%	9%	
Futronix		P400	L	NC	NC	NC	
Hamilton		H-LEDstat	T	5%	4%	4%	
Helvar	Digidim	452	T	7%	8%	7%	
Helvar	DigiDim	454	T	4%	4%	4%	
iLight		SCI 0405S	L	22%	20%	20%	
iLight		SCT 0405S	T	NC	NC	NC	
JUNG		225 NV	L	27%	27%	27%	
JUNG		225 TDE	T	17%	15%	15%	

SORAA PAR20 230V 11W - DIMMER COMPATIBILITY LIST - International

Manufacturer	Model	MD #	Edge Trigger	1 lamp Dim (%)	2 lamps Dim (%)	3 lamps Dim (%)	Comments
Legrand	CXM14	665114 14W3731	L	29%	25%	25%	
Legrand	HPM	450P		NC	NC	NC	(*)
Lumex	Load Smart Gen2	LT1D450LS	T	NC	NC	NC	(*)
Lutron	Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D	T	NC	NC	NC	
Lutron	Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D	L	NC	NC	NC	
Lutron		LP-RPM-4U-240	L	NC	NC	NC	
Lutron		LP-RPM-4A-230	T	4%	4%	4%	
Lutron	Grafik eye QS	QSGR-6PCE	L	NC	NC	NC	
Lutron	Grafik eye QS	QSGR-6PCE+NGRX-ELVI-CE	T	0%	0%	0%	
Lutron	Homeworks	LQSE-4A-D	T	NC	NC	NC	
Lutron	Homeworks	LQSE-4A-D	L	NC	NC	NC	
MARBO	Crabtree	DV21912	L	11%	11%	10%	
MK		K1501	L	NC	19%	19%	
MK		K1511	L	19%	20%	20%	
MK		K1522	L	NC	NC	NC	
MK	K1523WHILV	52470SL	L	NC	NC	NC	
MK		K1526	L	NC	NC	NC	
Mode Lighting	Evolution DDM-305-TE	EVO-S6P	L	NC	NC	NC	
Mode Lighting	Evolution DDM-305-TE	EVO-S6P	T	0%	0%	0%	
Osram		HTI DALI 315 DIM	T	8%	8%	8%	
Panasonic		WEG57813	L	7%	NC	NC	
Philips	Dynalite DDMC802GL	DGLED401	T	10%	10%	10%	
Philips	Dynalite DDMC802GL	DGLM402	L	NC	NC	NC	
Philips	Dynalite DDMC802GL	DGTM402	T	NC	NC	30%	

SORAA PAR20 230V 11W - DIMMER COMPATIBILITY LIST - International

Manufacturer	Model	MD #	Edge Trigger	1 lamp Dim (%)	2 lamps Dim (%)	3 lamps Dim (%)	Comments
Rako		RMT500 with remote control	T	0%	0%	0%	
Schneider		GD1G2W4	L	NC	11%	11%	
Siemens		5TC8 263	L	14%	12%	12%	
Trader	Dimpala	DIMR	T	5%	5%	5%	(*)
Trader	Dimpala	DIMPR	T	5%	5%	5%	(*)
Vossloh-Schwabe		nr. 553962	T	3%	3%	3%	(*)
Zano		ZGRID500	L	NC	NC	NC	

Notes:

Compatibility tests are conducted by Soraa (unless stated otherwise) only as guidance for the user

All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site

Results may vary due to variability in component choices and manufacturing processes by the dimmer manufacturer

Regards compatibility tests conducted by dimmer manufacturer, please contact the dimmer manufacturer or Soraa for more details and/or reports.

(*) Test results with this dimmer added to the compatibility list as of this Revision.

--%	Dims to < 20% (of the measured light output)
--%	Dims to 20-30% (of the measured light output)
NC	Not compatible (or dims to >30%)
Blank cell	Not tested