

# Eaton FAZ-D6/3-RT

Catalog Number: FAZ-D6/3-RT

Eaton FAZ branch protector,UL 1077 Industrial miniature circuit breaker - supplementary protector,High levels of inrush current are expected,6 A,15 kAIC,Three-pole,277/480 V,10-20X /n,50-60 Hz, Ring-tongue terminals,D Curve



## General specifications

<b>Product Name</b>	<b>Catalog Number</b>
Eaton FAZ branch protector	FAZ-D6/3-RT
<b>EAN</b>	<b>Product Length/Depth</b>
4015081021802	2 in
<b>Product Height</b>	<b>Product Width</b>
2 in	2.25 in
<b>Product Weight</b>	<b>Warranty</b>
0.85 lb	1 year
<b>Certifications</b>	<b>Catalog Notes</b>
IEC 60947-2 CSA Std. C22.2 No.235 UL 1077	Magnetic range for higher startup inrush levels that are usually seen in motors and transformers, and other high inductive systems.

## Physical Attributes

### Number of poles

Three-pole

### Terminals

Ring-tongue

## Performance Ratings

### Amperage Rating

6 A

### Trip Type

10-20X /n

## Resources

### Brochures

[Industrial miniature circuit breakers UL 489](#)

### Catalogs

[Eaton's Volume 4—Circuit Protection](#)

### Specifications and datasheets

[Product Data Sheet - FAZ-D6/3-RT](#)

[Eaton Specification Sheet - FAZ-D6/3-RT](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)