

Shown actual size: Diva preset dimmer and 1-gang Claro wallplate in White (WH).

86

#### **Product family features**

- Large paddle switch with a captive linear-slide dimmer for a standard designer wallplate opening
- Preset dimmer
- Select lighter color models feature built-in soft-glow locator light\*
- · C·L® and eco-dim® models available
- Coordinating Claro<sub>®</sub>, Satin Colors<sub>®</sub>, and Stainless Steel wallplates only available separately
- Custom engraving available for wallplates; see p. 237

#### **Control types**

Single-pole (one location)

0 0 0 3-way or 4-way (two or more locations)

#### **Direct load type compatibility**

Incandescent/halogen lighting

- ♥/♥ Dimmable CFL/LED lighting (screw-base)
- Electronic low-voltage lighting
- ∠ Fluorescent lighting
- LED lighting
- Switched lighting/fan/motor
- 🔀 Ceiling fans

#### Load type requiring load interface

Neon/cold cathode lighting

Lighting load interfaces may be applicable for some additional load type, voltage, and capacity combinations.

For additional information, see pp. 255-259.

\* Locator light not available in C·L and 0–10V dimmers, and fan controls

#### Available finishes

Use **BOLD** color code in model number (Example: DV-600P-**BR**) Gloss finishes\*







lvory



Gray



**BR** Brown



<u>BL</u> Black

Satin Colors® finishes\*



Match with separate Black (BL) or Midnight (MN) controls. For wallplate information, see p. 236

## Dimmers



- Paddle turns on/off
- Slide up to brighten, down to dim
- C-L<sub>®</sub> dimmers provide reliable dimming of dimmable CFLs/LEDs, as well as halogens and incandescents
- eco-dim<sub>®</sub> model guarantees at least 15% energy savings compared to a standard switch\*
- Locator light shines through paddle on select lighter colored models

#### ♀ Incandescent/halogen dimmers

### 🖞 / 🖥 Dimmable CFL/LED (screw-base) dimmers

#### 150W C·L dimmers

3-way/single-pole	DVCL-153P- <b>XX</b> 1
120V 600W (Inc) 150W (CFI	_/LED)
3-way/single-pole DVSCCL-153P-XX <sup>2</sup>	
120V 600W (Inc) 150W (CFI	_/LED)

Visit **www.lutron.com/dimcflled** for an approved list of dimmable CFL/LED bulbs, and how to calculate wattage when mixing lamp types. Adjustable low-end trim.

- Incandescent/halogen dimmers
- ♥/♥ Dimmable CFL/LED (screw-base) dimmers
- Hi-Lume 1% 2-wire LED driver dimmers

#### 250W C·L dimmers

3-way/single-pole	DVCL-253P- <b>XX</b> 1
120V 600W (Inc) 250W (CFL/LED)	
350W (Hi-lume 1% LED driver, max. 8)	
3-way/single-pole	DVSCCL-253P-XX2
120V 600W (Inc) 250W (CFL/LED)	
350W (Hi-lume 1% LED drive	r, max. 8)

Visit **www.lutron.com/dimcflled** for an approved list of dimmable CFL/LED bulbs, and how to calculate wattage when mixing lamp types. Adjustable low-end trim.

#### Incandescent/halogen dimmers

Dimmers
---------

Single-pole	DV-600P- <b>XX</b> 1
120V 600W	DVSC-600P- <b>XX</b> <sup>2</sup>
Single-pole	DV-10P- <b>XX</b> 1
120V 1000W	DVSC-10P- <b>XX</b> <sup>2</sup>
3-way	DV-603P- <b>XX</b> 1
120V 600W	DVSC-603P- <b>XX</b> <sup>2</sup>
3-way	DV-103P- <b>XX</b> 1
120V 1000W	DVSC-103P- <b>XX</b> <sup>2</sup>

#### eco-dim<sub>®</sub> dimmer

3-way/single-pole	DV-603PG- <b>XX</b> 3
120V 600W	

XX<sup>1</sup>: Gloss color codes, see p.87

88

- XX<sup>2</sup>: Satin Colors® codes, see p. 87
- **XX**<sup>3</sup>: Available in White (WH), Ivory (IV), Almond (AL) and Light Almond (LA) Wallplates not included. Order separately, see p. 236

All models must be derated if ganged unless otherwise noted, see pp. 250–252 and 254.

Maximum light output of 85% guarantees 15% energy savings over standard switches

#### $\nabla$ Magnetic low-voltage dimmers

#### Dimmers

Single-pole	DVLV-600P- <b>XX</b> 1
120V 600VA (450W)	DVSCLV-600P-XX2
Single-pole	DVLV-10P- <b>XX</b> 1
120V 1000VA (800W)	DVSCLV-10P-XX2
3-way	DVLV-603P- <b>XX</b> 1
120V 600VA (450W)	DVSCLV-603P-XX <sup>2</sup>
3-way	DVLV-103P- <b>XX</b> 1
120V 1000VA (800W)	DVSCLV-103P-XX2

The stated VA (Volt-Ampere) rating includes the magnetic transformer heat losses and the lamp load. The stated W (Watt) rating is the maximum lamp wattage based on assumed 20% transformer loss.

#### **Electronic low-voltage dimmer**

#### Dimmers\*

DVELV-300P-XX1
DVSCELV-300P-XX <sup>2</sup>
DVELV-303P- <b>XX</b> 1
DVSCELV-303P-XX <sup>2</sup>

XX<sup>1</sup>: Gloss color codes, see p. 87
 XX<sup>2</sup>: Satin Colors<sub>®</sub> codes, see p. 87
 Wallplates not included. Order separately, see p. 236

All models must be derated if ganged unless otherwise noted, see pp.250–252. \* Requires neutral wire connection

# ∠ () 2-wire fluorescent ballast/LED driver dimmers

# Dimmers\* 3-way/single-pole DVF-103P-XX<sup>1</sup> 120V 8A DVSCF-103P-XX<sup>2</sup> 3-way/single-pole DVF-103P-277-XX<sup>2</sup> 277V 6A DVSCF-103P-277XX<sup>2</sup>

For use with Hi-lume<sub>®</sub> 3D and EcoSystem<sub>®</sub> ballasts, and Hi-lume 1% and Hi-lume Premier 0.1% LED drivers. For more information on Hi-lume 1% LED drivers, visit www.lutron.com/hilumeLED. No derating required if ganged.

Adjustable low-end trim.

#### CE/ O-10V fluorescent/LED fixture dimmers (current sink control)

#### Dimmers\*

3-way/single-pole	DVSTV-XX1
120-277 V 50 mA max control curre	ent
3-way/single-pole DVSCSTV-XX	
120-277V 50mA max control curre	ent

No power pack required.

Dimmer has maximum capacity of 8A or 50mA 0–10V sink limited by whichever rating is achieved first.

Compatible with any IEC 60929 Annex E compliant ballast or driver, available from many manufacturers (check for IEC 60929 compliance on the specification of the designed ballast or driver, or confirm compatibility with the manufacturer).

Consult ballast/driver manufacturer for specific ballast/driver current draw to determine maximum number of ballasts/drivers per control. No derating required if ganged.

#### **∠**►/ <sup>(3)</sup> 0-10V fluorescent/LED fixture dimmers

(current sink control - power pack required)

Dimmers*	
Single-pole	DVTV- <b>XX</b> 1
30 mA max control current	
Single-pole	DVSCTV-XX <sup>2</sup>
30 mA max control current	

Control provides dimming signal only. For dimming with on/off switching, **use with Lutron Power Pack**: PP-DV or PP-347H.

Consult ballast/driver manufacturer for specific ballast/driver current draw to determine maximum number of ballasts/drivers per control.

Compatible with any IEC 60929 Annex E compliant ballast or driver, available from many manufacturers (check for IEC 60929 compliance on the specification of the designed ballast or driver, or confirm compatibility with the manufacturer).

No derating required if ganged.

#### **Tu-Wire**® fluorescent ballast dimmers

#### Dimmers

3-way/single-pole	DVFTU-5A3P-XX1
120V 5A	DVSCFTU-5A3P-XX2

Also compatible with Advance Mark X ballasts; for further information visit **www.lutron.com/advance**.

For information on use with Sylvania POWERSENSE ballasts, contact Technical Support at 1.800.523.9466.

XX<sup>1</sup>: Gloss color codes, see p. 87
 XX<sup>2</sup>: Satin Colors<sub>®</sub> codes, see p. 87
 Wallplates not included. Order separately, see p. 236

All models must be derated if ganged unless otherwise noted, see pp.250–252. \*Requires neutral wire connection

# Mechanical switches



- Paddle turns on/off
- Use with any 15A load
- General purpose
   switching of all light
   sources and motor loads
- Available with locator light

# Fan controls



- Paddle turns on/off
- Slide up to increase speed, down to decrease speed
- 3 quiet fan speeds for increased comfort
- For use with only one ceiling paddle fan
- Does not include
   locator light
- Designed to prevent
   motor hum

#### General purpose switches

#### Mechanical switches

CA-1PS- <b>XX</b> 1
SC-1PS- <b>XX</b> ²
CA-3PS- <b>XX</b> 1
SC-3PS- <u><b>XX</b></u> ²
CA-4PS-XX1
SC-4PS- <b>XX</b> <sup>2</sup>

#### Mechanical switches with locator light

Single-pole	CA-1PSNL- <b>XX</b> <sup>3</sup>
120V 15A	SC-1PSNL- <b>XX</b> ⁴
3-way	CA-3PSNL- <b>XX</b> 3
120V 15A	SC-3PSNL- <b>XX</b> ⁴
4-way	CA-4PSNL- <b>XX</b> <sup>3</sup>
120V 15A	SC-4PSNL- <b>XX</b> ⁴

Rated for: incandescent/halogen, magnetic low-voltage, electronic low-voltage, fluorescents, CFLs, LEDs, general purpose fans and motor loads.

No derating required if ganged.

#### **Fan controls**

#### Fan controls-quiet 3-speed

3-way/single-pole	DVFSQ-F-XX1
120V 1.5A	DVSCFSQ-F-XX2
3-way/single-pole	DVFSQ-F-HO-XX <sup>1</sup>
120V 2A	

DVFSQ-F-HO model for use with Hunter Original Series fans.

Does not include built-in locator light.

No derating required if ganged.

- XX<sup>2</sup>: Satin Colors® codes, see p.87
- XX<sup>3</sup>: Only available in Almond (AL), Ivory (IV), Light Almond (LA) and White (WH)
- XX<sup>4</sup>: Available in Biscuit (BI), Eggshell (ES), Goldstone (GS), Limestone (LS), Sea Glass (SG) and Snow (SW)

Wallplates not included. Order separately, see p. 236

**XX**<sup>1</sup>: Gloss color codes, see p.87

#### **Connections overview**



#### **Control types** (for 2 or more locations) Dim from one location, switch from the others



#### Fan control from one location, switch from the other



3-way 3-way Fan Control Switch\*\*

For more information on LED drivers, visit **www.lutron.com/LED**.

\*For illustration purposes only. Consult model number pages for specific voltage and capacity information.

\*\* For 3-way control and 4-way control, use 3-way dimmer/fan control with mechnical 3-way or 4-way switches

#### Load connections\* (continued)



#### Designer wallplate opening

# Diva<sub>®</sub> dimmers, switches, and fan controls

#### Accessories

#### **Wallplates**

4.75 in (121 mm)



Shown actual size: 2-gang Claro® wallplate in White (WH).

For more information about Designer wallplates, see p. 236.

.30 in  $(7.6 \, \text{mm})$ profile

#### **Coordinated electrical devices**





Tamper resistant, selftesting GFCI receptacle Customizable 6-port frame



For more information about coordinated Designer electrical devices, see p.237.

CUTRON. | 1.800.523.9466 | www.lutron.com/specificationguide Volume 1 P/N 367-1746 REV C

95