



250-PC

PANDUIT PART NUMBER	COPPER CONDUCTOR SIZE (AWG)		WIRE STRIP LENGTH (+ 1/32" -0")	INSTALLATION TOOLS & DIES (# OF CRIMPS) Die Index No.	
	MAIN	TAP		CT-920, CT-920CH CT-2930, CT-2931 CT-2920, CT-930 CT-930CH, CT-940CH* CT-2940*	CT-2001 CT-2002 CT-3001
CTAP4/0-4/0	#3/0 - #4/0 STR	#3/0 - #4/0 STR	1-1/4"	CD-920-D3 (1) PD3	-----
CTAP4/0-2/0	#3/0 - #4/0 STR	#1/0 - #2/0 STR	1-1/4"	CD-920-D3 (1) PD3	-----
CTAP4/0-2	#3/0 - #4/0 STR	#6 - #2 SOL OR STR	1-1/4"	CD-920-D3 (1) PD3	-----
CTAP2/0-2/0	#1/0 - #2/0 STR	#1/0 - #2/0 STR	1-1/16"	CD-920-0 (1) P0	-----
CTAP2/0-2	#1/0 - #2/0 STR	#8 - #2 SOL OR STR	1-1/16"	CD-920-0 (1) P0	-----
CTAP2-2	#2 SOL OR STR	#2 SOL OR STR	7/8"	CD-920-C (1) PC	CD-2001-C (2) PC
CTAP2-4	#2 SOL OR STR	#8 - #4 SOL OR STR	7/8"	CD-920-C (1) PC	CD-2001-C (2) PC
CTAP4-4	#4 SOL OR STR	#4 STR	3/4"	CD-920-BG (1) PBG	CD-2001-BG (1) PBG
CTAP4-6	#6 STR, #4 SOL OR STR	#6 SOL OR STR	3/4"	CD-920-BG (1) PBG	CD-2001-BG (1) PBG
CTAP4-8	#6 - #4 SOL OR STR	#8 SOL OR STR	3/4"	CD-920-BG (1) PBG	CD-2001-BG (1) PBG

\* CT-940CH and CT-2940 require CD-940-DA die adapter for CD-920 dies.



LISTED  
587H

For Instructions in Local Languages  
and Technical Support:

[www.panduit.com/resources/install\\_maintain.asp](http://www.panduit.com/resources/install_maintain.asp)

# PANDUIT

[www.panduit.com](http://www.panduit.com)

E-mail:  
[cs@panduit.com](mailto:cs@panduit.com)

Fax:  
708-444-6993