



| PART NUMBER | STRANDED COPPER CONDUCTOR SIZE (AWG) | | WIRE STRIP LENGTH (in.) | CRIMP DIE COLOR CODE | INSTALLATION TOOLS & DIES (# OF CRIMPS) | | | |
|-------------|--------------------------------------|----------------------|-------------------------|----------------------|---|----------------------------------|--|-----------------------------------|
| | RUN | TAP | | | CT-2001 DIE NO. (# OF CRIMPS) | CT-1700* (# OF CRIMPS) | CT-920, CT-920CH, CT-2920, CT-930, CT-930CH, CT-940CH**, CT-2940** DIE NO. (# OF CRIMPS) | |
| | | | | | | | | |
| CTAPF10-16 | 14 12 10 | 16-14 16-12 14 | 1/2 | RED | ---- | CD-2001-8 RED P21 (1) | RED P21 (2) | ---- |
| CTAPF8-12 | 10 8 | 10 12 | 11/16 | BLUE | ---- | CD-2001-6 BLUE P24 (1) | BLUE P24 (2) | ---- |
| CTAPF6-12 | 8 6 | 10-8 12-10 | 11/16 | GRAY | ---- | CD-2001-4 GRAY P29 (1) | GRAY P29 (2) | ---- |
| CTAPF4-12 | 6 5,4 | 8-6 12-8 | 1-5/16 | BROWN | CDM-2001-2 BROWN P33M (1) | CD-2001-2 BROWN P33 (2) | BROWN P33 (4) | CDM-920-2 BROWN P33M (1) |
| CTAPF3-12 | 5,4 3 | 6-5 12-6 | 1-5/16 | GREEN | CDM-2001-1 GREEN P37M (1) | CD-2001-1 GREEN P37 (2) | GREEN P37 (4) | CDM-920-1 GREEN P37M (1) |
| CTAPF2-12 | 4 3 2 | 4 5 12-6 | 1-5/16 | PINK | CDM-2001-1/0 PINK P42M (1) | CD-2001-1/0 PINK P42 (2) | ---- | CDM-920-1/0 PINK P42M (1) |
| CTAPF1-12 | 3 2 1 | 4-3 5-4 12-5 | 1-7/8 | BLACK | CDM-2001-2/0 BLACK P45M (2) | CD-2001-2/0 BLACK P45 (3) | ---- | CDM-920-2/0 BLACK P45M (1) |
| CTAPF1/0-12 | 2 1 1/0 | 4-2 4-3 12-4 | 1-7/8 | ORANGE | CDM-2001-3/0 ORANGE P50M (2) | CD-2001-3/0 ORANGE P50 (3) | ---- | CDM-920-3/0 ORANGE P50M (1) |
| CTAPF2/0-12 | 1 1/0 2/0 | 2-1 3-2 12-3 | 1-7/8 | PURPLE | ---- | CD-2001-4/0 PURPLE P54 (3) | ---- | CDM-920-4/0 PURPLE P54M (1) |
| CTAPF3/0-12 | 1/0 2/0 3/0 | 1-1/0 2-1 12-2 | 1-7/8 | YELLOW | ---- | CD-2001-250 YELLOW P62 (3) | ---- | CDM-920-250 YELLOW P62M (1) |

* CT-1700 crimp die pockets are integrated into the tool head
 ** CT-940CH and CT-2940 require CD-940-DA adapter for CDM-920 dies

