

### **Application Note**

# 1606-XLP30E with DC 24...28V/30 W



- Mounted and connected in record time, no tools required
- for industry
- Tiny:  $WxHxD = 45 \times 75 \times 91$ mm
- Output voltage adjustable to DC 28V

- 100...240V Wide Range Input (AC 85...264V permitted)
- Exceptional Overload Design (no switch off at overload but up to 1.5 times nominal current)

• Input	
Input voltage	AC100240V (Wide Range), 4763Hz Admiss. limits: AC 85264V (DC 85375V)
Input current	<0.6A (@ AC 100V, 30W P <sub>out</sub> ) <0.35A (@ AC 196V, 30W P <sub>out</sub> )
External Fusing	Unit has internal (not accessible) input fuse. No other protection required. In order to meet local requirements, please consult local codes and regulations for proper installation.
Transient immunity	Transient resistance acc. to VDE 0160 / W2 (750V / 1.3ms), over entire load range
Hold-up time (see diagram below)	>190ms bei AC 230V, 24V / 1.3A >107ms @ AC 196V, 24V / 1.3A >19ms @ AC 100V, 24V / 1.3A

• Efficiency, Reliability			
Efficiency	typ. 87.5%	(AC 230V, 24V / 1.3A)	
	(see also dia	gram below)	
Losses	typ. 4.5W	(AC 230V, 24V / 1.3A)	
MTBF (Reliability)	ca. 650.000h acc. to Siemensnorm SN 29500		
	(24V/1.3 A,	AC 230V, $T_{amb} = +40^{\circ}C$ )	

Prior to shipment, every unit undergoes the following tests in order to isolate any defective units which might suffer an early failure:

- Run-in / burn-in (Full load,  $T_{amb} = +60$ °C, on/off cycle)
- Functional test (100%)

~				
A Come	twination	Mechan	ioa mata	II oftion
• Cons	H M I C M H ( I ) I P	MISHINII	ICS. IIISIM	

Robust plastic housing (US Patent No. D442, 923S), fine ventilation grid on three housing sides to keep out small parts (e.g. screws), IP20

Dimensions and weight

Ventilation/Cooling

BxHxT 45mm x 75mm x 91mm (+ DIN Rail) Depth incl. terminals: 98mm (+ DIN Rail) Weight

Mounting orientation , or (cf. 'Output')

Normal convection, no fan required Free space f. cooling recommended: 25mm on sides with ventilation grid

Easy snap-on mounting onto the DIN-Rail (TS35/7,5 or TS35/15). Unit sits safely and firmly on the rail; no tools required even to remove

Connection by Spring Clamp terminals; uniformly firm hold, vibra-

tion-resistant and maintenance-free:

2 terminals per output

Wire strip length 6mm (0.24in) recommended

Wire Size Input/Output Stranded 28...12 AWG (0.3...2.5 mm<sup>2</sup>),

Solid 28...12 AWG (0.3...4 mm<sup>2</sup>)

Design details - for your advantage:

- All terminals are easy to reach as mounted on the front panel.
- Input and output are strictly apart from each other (input below, output above) and so cannot be mixed up
- Mounting and connection do not require any screwdriver
- → Easy, quick, durable and reliable installation



• Output	
Output voltage • preset	DC 2428V, adj. by front panel potentiometer $24.5V \pm 0.5\%$
Voltage regulation	static 0.5% $V_{out}$ , dynamic ±2% $V_{out}$ overall
Ripple/Noise	$<$ 50mV <sub>PP</sub> (20MHz bandwidth, 50 $\Omega$ -measurement)
Overvoltage prot. (OVP)	<40V
Output noise suppression	Radiated EMI values below EN50081-1, even when using long (>2m), unscreened output cables
Rated continuous loading	up to 1.3A (convection cooling) depending on built-in orientation, V <sub>in</sub> and T <sub>amb</sub> ; for details see derating diagram below
Overload behavior	No switch-off at overload/short-circuit, instead: up to $1.5 \cdot I_{\rm rated.}$ So you need no oversizing to start awkward loads.
Protection	Unit is protected against (also permanent) short-circuit, overload and open-circuit
Derating	depending on built-in orientation; see diagram below
Parallel operation	Yes
Power back immunity	35V
Operation indicator	Green LED (DC ON)


• Environmenta	l Data, EMC, Safety		
Ambient temperature range (measured 25mm below unit)			
<ul> <li>storage, transport</li> </ul>	-25°C +85°C		
<ul> <li>operation</li> </ul>	-10°C +70°C (for derating see diagram below)		
Humidity	max. 95% (without condensation)		
Electromagnetic	EN 50081-1 (includes EN 50081-2)		
emissions (EME)	Class B (EN 55011, EN 55022) incl. Annex A thanks to noise suppression		
Electromagnetic	EN 61000-6-2 (includes EN 55024)		
immunity (EMI)			
Safe low voltage:	SELV (EN60950, VDE0100/T.410), PELV (EN50178)		
Prot. class/degree:	Class I (EN60950) / IP20 (EN60529)		
The PSU complies with all major <b>safety approvals</b> for EU (EN 60 950,			

EN 60204-1, EN 50178), USA (UL 60950, E137006, UL508 LISTED, E198865), Canada (CAN/CSA-C22.2 No 60950 [CUR], CAN/CSA-C22.2 No. 14 [CUL]).


**Operation on IT networks:** The unit is designed to operate on IT networks. The unit may still deliver a hazardous voltage after the fuses are tripped.

#### Diagrams


## Output characteristic $V_{out}/I_{out}$ (min.)




# Efficiency (@ V<sub>out</sub> = 24V, typ.)



## Derating of output power



# Hold-up time with ACin (@ $V_{out} = 24V$ , typ. + min.)



 $Specifications\ valid\ for\ 230V\ AC\ input\ voltage, +25^{\circ}C\ ambient\ temperature, and\ 5\ min\ run-in\ time,\ unless\ otherwise\ stated.\ They\ are\ subject\ to\ change\ without\ prior\ notice.$ 

#### www.rockwellautomation.com

#### Corporate Headquarters

Rockwell Automation, 777 East Wisconsin Avenue, Suite 1400, Milwaukee, WI, 53202-5302 USA, Tel: (1) 414.212.5200, Fax: (1) 414.212.5201

#### Headquarters for Allen-Bradley Products, Rockwell Software Products and Global Manufacturing Solutions

Americas: Rockwell Automation, 1201 South Second Street, Milwaukee, WI 53204-2496 USA, Tel: (1) 414.382.2000, Fax: (1) 414.382.4444 Europe: Rockwell Automation SA/NV, Vorstlaan/Boulevard du Souverain 36-BP 3A/B, 1170 Brussels, Belgium, Tel: (32) 2 663 0600, Fax: (32) 2 663 0640 Asia Pacific: Rockwell Automation, 27/F Citicorp Centre, 18 Whitfield Road, Causeway Bay, Hong Kong, Tel: (852) 2887 4788, Fax: (852) 2508 1846

#### Headquarters for Dodge and Reliance Electric Products

Americas: Rockwell Automation, 6040 Ponders Court, Greenville, SC 29615-4617 USA, Tel: (1) 864.297.4800, Fax: (1) 864.281.2433 Europe: Rockwell Automation, Brühlstraße 22, D-74834 Elztal-Dallau, Germany, Tel: (49) 6261 9410, Fax: (49) 6261 1774 Asia Pacific: Rockwell Automation, 55 Newton Road, #11-01/02 Revenue House, Singapore 307987, Tel: (65) 351 6723, Fax: (65) 355 1733