

## M9100E-DPS OPERATING INSTRUCTIONS

### ACSI M1520M-DPS

Mortise Lock with Door Position Sensor (DPS).

#### DPS – DOOR POSITION MONITORING

Monitors the door position. A magnetic sensor mounted in the mortise lock reacts to the proximity of a magnet mounted behind the ASA strike.

#### ELECTRICAL SPECIFICATIONS

SPDT Magnetic Reed Switch

VOLTAGE                      CURRENT

28 VDC                          0.3 A

NOTE: Mainly used as a dry contact monitoring switch.

#### WIRING DIAGRAM

**WHITE WIRE** – Common

**RED WIRE** – Open Loop Secure

**GREEN WIRE** – closed Loop Secure

