

a xylem brand

JOB:

UNIT TAG: ENGINEER: CONTRACTOR: **REPRESENTATIVE:**

ORDER NO. SUBMITTED BY:

APPROVED BY:



Iron & Lead-Free[†] Bronze^{*} Booster Pump

*Where potable water is supplied, use a lead-free[†] bronze pump.

DESCRIPTION

Bell & Gossett in-line three-piece booster pumps are designed for hydronic systems. Series 100 and HV are Listed with Underwriter's Laboratories.

CONSTRUCTION

Body: Cast Iron or Lead-Free[†] Bronze

Seal: Mechanical. Carbon on Ceramic

Shaft: Carbon Steel. Heat Treated

Pump and Motor Bearings:

-All except PD-38 and PD-40: Bronze Sleeve, Oil Lubricated -PD-38 and PD-40: Ball Bearing, Permanently Lubricated

Coupler:

-All except PD38 and PD40: Flexible, Spring type

-PD38 and PD40: Flexible, sleeve type.

Motor: Bell & Gossett 1/12 hp thru 1-1/2 hp standard single and three phase dripproof motors are Recognized under the Component Program of Underwriter's Laboratories, Inc. Bell & Gossett boosters with their respective Bell & Gossett manufactured standard 60 hertz single and three phase motors are Certified by CSA.

OPERATIONAL DATA

Maximum Working Pressure: 125 PSI (682 kPa)

Maximum Operating Temperature:

Standard Seal: 225°F (107°C) continuous Special Seals: 250°F (121°C) continuous (consult local B&G Representative)

Maximum Motor RPM: 1750

IMPELLER: PUMP MODEL NO. Series 100® Pump Series HV & 2 PR, 2-1/2, LD3

HD3, PD35, PD

PD38 & PD40

IRON BODY

DEL NO.		DIVONZE DODI
® Pump	Polypropylene* or Lead-Free [†]	Polypropylene* or
	Brass	Lead-Free [†] Brass
& 2	Phenolic* or Lead-Free [†] Brass	Phenolic* or Lead-
		Free [†] Brass
LD3	Steel, Zinc Plated or Lead-Free [†]	Lead-Free [†] Brass
	Brass	
5, PD37	Steel, Zinc Plated or Lead-Free [†]	Lead-Free [†] Brass
	Brass	2000 1100 21000
040	Cast Iron or Lead-Free [†] Brass	Lead-Free [†] Brass
	Cast non of Lead-Free Blass	LCau-IICE DIa35

* System temperatures above 225 °F (107 °C) require a brass impeller.

[†] Contains less than 0.25% Lead content by weight on wetted surfaces.



SCHEDULE

	FLANGE		**STANDARD 60 CYCLE CHARACTERISTICS					QUANTITY			
MODEL	SIZE NPT							Iron Body		Bronze Body	
NO.	INCHES	HP	PH	VOLTAGE [*]	F.L. AMPS	RPM	TAGGING INFORMATION	STD	BI	BI	NFI
Series 100	3/4, 1, 1-1/4 & 1-1/2	1/12	1	115	1.75	1725					
Series PR	3/4, 1, 1-1/4 & 1-1/2	1/6	1	115	1.9	1725					-
Series HV	1, 1-1/4 & 1-1/2	1/6	1	115	1.9	1725					
2	2	1/6	1	115	1.9	1725		1			
2-1/2	2-1/2	1/4	1	115	3.0	1725					-
LD3	3	1/4	1	115	3.0	1725					-
HD3	3	1/3	1	115/230	4.2/2.1	1725					-
PD-35S	3	1/2	1	115/230	5.2/2.6	1725					-
PD-35T	3	1/2	3	208-230/460	1.8-1.7/.85	1750					-
PD-37S	3	3/4	1	115/230	7.0/3.5	1725					-
PD-37T	3	3/4	3	208-230/460	2.45-2.4/1.2	1750					-
PD-38S	3	1	1	115/230	9.8/4.5	1725					-
PD-38T	3	1	3	208-230/460	3.4-3.4/1.7	1725					-
PD-40S	3	1-1/2	1	115/230	18.0/9.0	1725					-
PD-40T	3	1-1/2	3	208-230/460	4.8-4.8/2.4	1725					-

**Motors with special electrical characteristics are available on request at additional cost.

^{*}1 PH Motors: Built-in overload protection

3 PH Motors: Overload protection must be provided

Bell & Gossett Booster Pumps equipped with a drip-proof motor are recommended for indoor use only.



SUBMITTA

BRONZE BODY

A-120H

DATE: DATE: DATE:

Iron & Bronze Booster Pump Submittal



JELIV	LUI	114 07	LEONG	 (cricine)
ΩV	011		-	

					APPROX. SHPG.		
	FLANGE	DIMENSIONS IN INCHES (MM)			WT. LBS. (Kg)		
MODEL	SIZE NPT				IRON	BRONZE	
NO.	INCHES	Α	В	C	BODY	BODY	
Series 100	3/4, 1,	14-7/8	6-3/8	12-3/4	20	21	
Series 100	1-1/4 & 1-1/2	(378)	(162)	(324)	(9)	(10)	
Series PR	3/4, 1,	15-1/4	8-1/2	12-3/4	30	32	
Selles FR	1-1/4 & 1-1/2	(387)	(216)	(324)	(14)	(15)	
Series HV	1,	15-3/8	8-1/2	13	28	30	
Selles ITV	1-1/4 & 1-1/2	(391)	(216)	(330)	(13)	(14)	
2	2	16-5/8	8-1/2	14	36	39	
2	2	(422)	(216)	(356)	(16)	(18)	
2-1/2	2-1/2	17-1/4	10	14	54	58	
2-1/2	2-1/2	(438)	(254)	(356)	(24)	(26)	
LD3	3	17-1/4	10	14	53	57	
LDJ	3	(438)	(254)	(356)	(24)	(26)	
HD3	3	17-1/2	10	14-1/4	55	59	
1100	, v	(444)	(254)	(362)	(25)	(27)	
PD-35S	3	20-1/4	12	16-7/8	75	80	
1 8-000	Ů	(514)	(305)	(429)	(34)	(36)	
PD-35T	3	20-1/4	12	16-7/8	75	80	
1 8-001	, v	(514)	(305)	(429)	(34)	(36)	
PD-37S	3	20-1/4	12	16-7/8	75	80	
10-0/0	, v	(514)	(305)	(429)	(34)	(36)	
PD-37T	3	20-1/4	12	16-7/8	75	80	
1 0 0/1	Ů	(514)	(305)	(429)	(34)	(36)	
PD-38S	3	22-11/16	14-1/2	18-15/16	128	138	
1 8 000	Ŭ	(576)	(368)	(481)	(58)	(63)	
PD-38T	3	23-15/16	14-1/2	20-3/16	125	135	
1 8 001	Ľ	(608)	(368)	(513)	(57)	(61)	
PD-40S	3	24-3/4	14-1/2	21	130	140	
10-400		(629)	(368)	(533)	(59)	(64)	
PD-40T	3	21-7/8	14-1/2	18-1/8	127	137	
10-401	3	(556)	(368)	(460)	(58)	(62)	

Dimensions are subject to change.

Not to be used for construction purposes unless certified.



xylem

Bell & Gossett is a trademark of Xylem Inc. or one of its subsidiaries. \circledast 2012 Xylem Inc.

#1	#2	#3	#4
115 & 230Volt 60Hz 1PH 110 & 220Volt 50Hz 1PH	-	-	-
115 & 230Volt 60Hz 1PH 110 & 220Volt 50Hz 1PH	-	3PH	-
-	1PH	-	-
-	-	ALL	-
_	-	-	ALL
	115 & 230Volt 60Hz 1PH 110 & 220Volt 50Hz 1PH 115 & 230Volt 60Hz 1PH	115 & 230Volt 60Hz 1PH - 110 & 220Volt 50Hz 1PH - 115 & 230Volt 60Hz 1PH - 115 & 230Volt 50Hz 1PH -	115 & 230Volt 60Hz 1PH - - 110 & 220Volt 50Hz 1PH - - 115 & 230Volt 60Hz 1PH - 3PH 110 & 220Volt 50Hz 1PH - 1PH 110 & 220Volt 50Hz 1PH - 1PH

Electrical Box Arrangement for pumps with B&G Manufactured Motors

SUCTION

DISCHARGE

TYPICAL SPECIFICATIONS

MODEL

2

The Contractor shall furnish and install In-The-Line pumps as illustrated on the plans and in accordance with the following specifications:

1. The pumps shall be of the horizontal, oil-lubricated type. (Except PD-38, PD-40 are permanently lubricated) Specifically designed and guaranteed for quiet operation. Suitable for 125# (862 kPa) working pressure.

2. The pumps shall have a ground and polished steel shaft with a hardened integral thrust collar. The shaft shall be supported by two horizontal sleeve bearings designed to circulate oil. (Except PD-38, PD-40 are grease lubricated ball bearing design) The pumps are to be equipped with a mechanical seal with carbon seal face rotating against a ceramic seat. The motor shall be non-overloading at any point on pump curve.

3. The motor shall be of the drip-proof, sleeve-bearing, (Except PD-38, PD-40 are ball bearing) quiet operating, rubber-mounted construction. Motors shall have built-in thermal overload protectors. (Exception - PD models with 3-phase motors, see paragraph 4.)

4. For PD models with 3-phase motors, add the following: The Contractor shall furnish and install a magnetic starter for each booster pump with at least two thermal overload protectors. The starter shall be equipped with manual reset buttons.

All Units must be ITT Bell & Gossett Model No. _____, or approved equal with capacity of _____GPM at _____ft. head when directly driven through a self aligning flexible coupling by an oil lubricated motor, _____volts ____cycle___phase.