

CONTACT US @ 855-355-2724 E-Mail: <u>Sales@brahelectric.com</u> www.Brahelectric.com

PRODUCT DATA SHEET



MAGNETIC CONTACTOR

PART NUMBER – BA16-30-10-80: BRAH Electric, aftermarket direct replacement contactors for ABB A16-30-10-80, A-Line series, type A, 3P, 3PH, 17A, 600V, 5HP @ 240V, 10HP @ 480V, 15HP @ 600V, complete with 220/240V AC coil, and 1 N/O auxiliary contact, AC magnetic contactor, suitable for use with A-Line series motor control systems

PRODUCT SPECIFICATIONS

PART NO. BA16-30-10-80		ΤΥΡΕ	VALUE (UNITS)	NOTES	COMMENTS
Voltage Selection Charts BA16-XXXX		PHASE	3		
		POLES	3		
BA16-30-10	120V AC				
BA16-30-10-42	277V AC	VOLTAGE	600 (VAC)		
BA16-30-10-51	480V AC				
BA16-30-10-55	500/600V AC	AMPERAGE	17 (A)		
BA16-30-10-80	240V AC	COIL VOLTAGE MIN			
BA16-30-10-81	24V AC		220 (VAC)		
BA16-30-10-83	48V AC				
BA16-30-10-84	120V AC	COIL VOLTAGE MAX	240 (VAC)		
BA16-30-10-86	415/440V AC	MIN HP. RATING	5 (HP)	@ 240V	
			- (/	C =	
		MAX HP RATING	15 (HP)	@ 600V	

Warranty: All Products sold by BRAH Electric are guaranteed to be free of defect for a period of one year, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric.

