E-Mail: Sales@brahelectric.com

www.Brahelectric.com

PRODUCT DATA SHEET



<u>PART NUMBER – BA40-30-10</u>: BRAH Electric, contactors, aftermarket direct replacement contactors for ABB A40-30-10, A-Line series, type A, 3P, 3PH, 42A, 600V, 15HP @ 240V, 30HP @ 480V, 40HP @ 600V, complete with 120V AC coil, and 1 N/O auxiliary contact, AC magnetic contactor, suitable for use with A-Line series motor control systems

PRODUCT SPECIFICATIONS


MAGNETIC CONTACTOR PART NO. BA 40-30-10

Voltage Selection Charts BA40-XXXX


120V AC
277V AC
480V AC
500/600V AC
220/240V AC
24V AC
48V AC
120V AC
415/440V AC

TYPE	VALUE (UNITS)	NOTES	COMMENTS
PHASE	3		
POLES	3		
VOLTAGE	600 (VAC)		
AMPERAGE	42 (A)		
COIL VOLTAGE MIN	120 (V)		
COIL VOLTAGE MAX	120 (V)		
MIN HP. RATING	15 (HP)	@ 240V	
MAX HP RATING	40 (HP)	@ 600V	

Warranty: All Products sold by BRAH Electric are guaranteed to be free of defect for a period of one year, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric.



IS AN AFTERMARKET DIRECT REPLACMENT FOR ABB A40-30-10, A-LINE SERIES. SUITABLE FOR USE WITH A-LINE SERIES MOTOR CONTROL SYSTEMS



PROPRIETARY AND CONFIDENTIAL

THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF BRAH ELECTRIC. ANY REPRODUCTION IN PART OR AS A WHOLE WITHOUT THE WRITTEN PERMISSION OF BRAH ELECTRIC IS PROHIBITED.

METRIC UNITS ARE DISPLAYED BENEATH IN [MM.]

MOLDED PLASTIC CASE FINISH

N/A

DO NOT SCALE DRAWING



MAGNETIC CONTACTOR

SIZE DWG. NO. Α BA40-30-10 Α SCALE:1:3 WEIGHT: SHEET 1 OF 1