

CONTACT US @ 855-355-2724 E-Mail: <u>Sales@brahelectric.com</u> www.Brahelectric.com

PRODUCT DATA SHEET



BLC2D1810-Q6

BLC2D1810-Q7

BLC2D18D10-R7

BLC2D1810-T6

BLC2D1810-U6

BLC2D1810-U7

380 VAC

380 VAC

440 VAC

480 VAC

240 VAC

240 VAC

PART NUMBER – BLC2D1810-Q7: BRAH Electric, aftermarket direct replacement contactors for Telemecanique LC2D1810-Q7, TeSys D, direct substitute contactor, type LC2D, 3P, 3PH, 32A, 600V, 5HP @ 240V, 10HP @ 480V, 15HP @ 600V, complete with 380V AC coil, 1 N/O auxiliary contact, AC magnetic contactor suitable for use with LC2D series motor control systems

MAGNETIC CONTACTOR		ΤΥΡΕ	VALUE (UNITS)	NOTES	COMMENT
PART NO. BLC2D1810-Q7		PHASE	3		
Voltage Selection Chart		POLES	3		
BLC2D18XX		VOLTAGE			
BLC2D18	110/120 VAC	VOLIAGE	600 (VAC)		
BLC2D1810	110/120 VAC	AMPERAGE	32 (A)		
BLC2D1810-B6	24 VAC		280 (1/)		
BLC2D1810-B7	24 VAC	COIL VOLTAGE MAX	380 (V)		
BLC2D1810-G6	110/120 VAC	MIN HP. RATING	5 (HP)	@ 240V	
BLC2D1810-G7	110/120 VAC	MAX HP. RATING	15 (HP)	@ 600V	
BLC2D1810-M6	220 VAC				1
BLC2D1810-M7	220 VAC				

PRODUCT SPECIFICATIONS

Warranty: All Products sold by BRAH Electric are guaranteed to be free of defect for a period of one year, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric

		REVISIONS					
	ZOI	NE REV. DESC	RIPTION	DATE	APPROVED		
MOUNTING		DAD SIDE WIRE TER TION OF FUNCTION OPS FOR ATTACH MOUNTED ACC	<u>IN MARKER</u>				
1.26 0.61 [32.1] [15.4] 1.59 [40.4] 0.27 [6.8] 1.59 [40.4] 0.27 [6.8]					R0.10 [2.5] Ø 0.18 [4.5] 88 7.7] 0.19 [4.9] Ø 0.19 [4.7]		
	4.12 [104.6]	0.51 [13.0] 1.80 [45.8]					
*NOTE: BRAH ELECTRIC CONTACTOR BLC2D1810-Q7 IS AN AFTERMARKET DIRECT REPLACMENT FOR LC2D1810-Q7,LC2-D SERIES. SUITABLE FOR USE WITH LC2-D SERIES MOTOR CONTROL SYSTEMS	THIRD ANGLE PROJECTION THIRD ANGLE PROJECTION PROPRIETARY AND CONFIDENTIAL THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF BRAH ELECTRIC. ANY REPRODUCTION IN PART OR AS A WHOLE WITHOUT THE WRITTEN PERMISSION OF BRAH ELECTRIC IS PROHIBITED.	UNLESS OTHERWISE NOTED ALL DIMENSIONS ARE IN INCHES METRIC UNITS ARE DISPLAYED BENEATH IN [MM.] MATERIAL MOLDED PLASTIC CASE FINISH N/A DO NOT SCALE DRAWING	SIZE DWG. NO.	BRA lect TIC CON C2D1810 HT: 3.2LBS			