

CONTACT US @ 855-355-2724 E-Mail: <u>Sales@brahelectric.com</u> www.Brahelectric.com

## **PRODUCT DATA SHEET**



BLC2D3210-Q6

BLC2D3210-R7

BLC2D3210-T6

BLC2D3210-U6

BLC2D3210-U7

380 VAC

440 VAC

480 VAC

240 VAC

240 VAC

**PART NUMBER – BLC2D3210-UG**: BRAH Electric, aftermarket direct replacement contactors for Telemecanique LC2D3210-U6, TeSys D Series, type LC2D, 3P, 3PH, 50A, 600V, 10HP @ 240V, 20HP @ 480V, 30HP @ 600V, complete with 240V AC coil, 1 N/O auxiliary contact, AC magnetic contactor, suitable for use with LC2-D series motor control systems

## **PRODUCT SPECIFICATIONS**

MAGNETIC CONTACTOR		ΤΥΡΕ	VALUE (UNITS)	NOTES	COMMENTS
PART NO. BLC2D3210-U6		PHASE	3		
Voltage Selection Chart BLC2D32XX		POLES	3		
BLC2D32	110/120 VAC	VOLTAGE	600 (VAC)		
BLC2D3210	110/120 VAC	AMPERAGE	50(A)		
BLC2D3210-B6	24 VAC	COIL VOLTAGE MAX			
BLC2D3210-B7	24 VAC		240 (V)		
BLC2D3210-G6	110/120 VAC	MIN HP. RATING	10 (HP)	@ 240V	
BLC2D3210-G7	110/120 VAC	MAX HP RATING	20 (110)	@ C00V	
BLC2D3210-M6	220 VAC		30 (HP)	@ 600V	
BLC2D3210-M7	220 VAC	-			

Warranty: All Products sold by BRAH Electric are guaranteed to be free of defect for a period of one year, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric

	REVISIONS   ZONE REV. DESCRIPTION DATE APPROVED		
MOUNTING FIXTURES MOUNTING HOLES	LOAD SIDE WIRE TERMINALS		
	$\begin{array}{c} R0.10\\ 2.86\\ 72.7] \\ \hline \\ 2.80\\ 71.2] \\ \hline \\ \\ 0.22\\ 5.6] \\ \hline \\ \\ 0.22\\ 5.6] \\ \hline \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ $		
4.12 [104.6]	0.51 [13.0] 1.80 [45.8]		
*NOTE: BRAH ELECTRIC CONTACTOR BLC2D3210-U6 IS AN AFTERMARKET DIRECT REPLACMENT FOR LC2D3210-U6,LC2-D SERIES. SUITABLE FOR USE WITH LC2-D SERIES MOTOR CONTROL SYSTEMS	TIAL N THIS OF TION JT THE MATERIAL MOLDED PLASTIC CASE FINISH N/A SIZE DWG. NO. BI C2D3210-U6		