

Current Setting by DIP Switch



For example: LCM-40BLE Current settings

Extra settings

Io \ DIP S.W.	1	2	3	4	5	6	Max. LED voltage
350mA	----	----	----	----	----	----	100V
500mA	ON	----	----	----	----	----	80V
600mA	ON	ON	----	----	----	----	67V
700mA(factory default)	ON	ON	ON	----	----	ON	57V
900mA	ON	ON	ON	ON	----	ON	45V
1050mA	ON	ON	ON	ON	ON	ON	40V

Io \ DIP S.W.	1	2	3	4	5	6	Max. LED voltage
450mA	----	ON	----	----	----	----	78V
550mA	----	----	----	ON	----	----	73V
650mA	ON	----	----	----	ON	----	62V
750mA	ON	ON	----	----	ON	ON	53V
800mA	ON	ON	----	ON	----	ON	50V
850mA	ON	ON	ON	----	ON	ON	47V
950mA	ON	ON	----	ON	ON	ON	42V

LCM-60.

Extra settings

Io \ DIP S.W.	1	2	3	4	5	6
500mA	----	----	----	----	----	----
600mA	ON	----	----	----	----	----
700mA(factory default)	ON	ON	----	----	----	----
900mA	ON	ON	ON	----	----	ON
1050mA	ON	ON	ON	ON	----	ON
1400mA	ON	ON	ON	ON	ON	ON

Io \ DIP S.W.	1	2	3	4	5	6	Max. LED voltage
600mA	----	ON	----	----	----	----	93V
660mA	----	----	----	ON	----	----	93V
950mA	ON	----	----	----	ON	----	93V
1050mA	ON	ON	----	----	ON	ON	69V
860mA	ON	ON	----	ON	----	ON	69V
1250mA	ON	ON	ON	----	ON	ON	69V
1200mA	ON	ON	----	ON	ON	ON	69V

Strøm mA			1	2	3	4	5	6	Max Vout ubelastet 700		
LCM25	LCM40	LCM60							LCM25	LCM40	LCM60
1050	1050	1400	ON	ON	ON	ON	ON	ON	41	65	76
900	900	1300		ON	ON	ON	ON	ON			
950	975	1300	ON		ON	ON	ON	ON			
700	825	1200			ON	ON	ON	ON			
950	970	1200	ON	ON		ON	ON	ON			
730	800	1100		ON		ON	ON	ON			
850	870	1100	ON			ON	ON	ON			
600	700	1000				ON	ON	ON			
859	870	1250	ON	ON	ON		ON	ON			
630	700	1150		ON	ON		ON	ON			
675	770	1150	ON		ON		ON	ON			
560	600	1050			ON		ON	ON			
670	770	1050	ON	ON			ON	ON			
550	600	950		ON			ON	ON			
600	650	950	ON				ON	ON			
485	500	850					ON	ON			
910	900	1050	ON	ON	ON	ON		ON	41	65	76
700	750	950		ON	ON	ON		ON			
740	800	950	ON		ON	ON		ON			
620	650	850			ON	ON		ON			
750	800	850	ON	ON		ON		ON			
620	650	750		ON		ON		ON			
650	700	750	ON			ON		ON			
540	550	660				ON		ON			
660	700	900	ON	ON	ON			ON	41	65	76
540	550	800		ON	ON			ON			
580	600	800	ON		ON			ON			
460	450	700			ON			ON			
600	600	700	ON	ON				ON			
460	450	600		ON				ON			
500	500	600	ON					ON			
350	350	500						ON			
1050	1050	1100	ON	ON	ON	ON	ON			110	
900	900	1100		ON	ON	ON	ON				
950	975	1100	ON		ON	ON	ON				
700	825	1200			ON	ON	ON				
950	970	1200	ON	ON		ON	ON				
730	800	1100		ON		ON	ON				
850	870	1100	ON			ON	ON				
600	700	1000				ON	ON				
859	870	1050	ON	ON	ON		ON				
630	700	1050		ON	ON		ON				
675	770	1050	ON		ON		ON				
560	600	1050			ON		ON				
670	770	1050	ON	ON			ON				
550	600	950		ON			ON				
600	650	950	ON				ON				
485	500	850					ON				
910	900	1050	ON	ON	ON	ON					
700	750	950		ON	ON	ON					
740	800	950	ON		ON	ON					
620	650	850			ON	ON					
750	800	850	ON	ON		ON					
620	650	750		ON		ON					
650	700	750	ON			ON					
540	550	660				ON					
660	700	900	ON	ON	ON						
540	550	800		ON	ON						
580	600	800	ON		ON						
460	450	700			ON						
600	600	700	ON	ON					59	110	102
460	450	600		ON							
500	500	600	ON						59	110	102
350	350	500							59	110	102