

Usage of D-Series on copper conductor

Connector D-Series

D-Series connector	cross section in mm ² for copper conductor class 5						
description	1,5	2,5	4	6	8	10	16
D1,5-16 SV(-T/-S)-V(-K)	without sleeve						

D-Series connector	cross section in mm ² for copper conductor class 5								
description	1,5	2,5	4	6	8	10	16	25	35
D1,5-35 SV(-T/-S)-V(-K)	without sleeve								
D10-35 SV(-T/-S)-V(-K)						without sleeve			

D-Series connector	cross section in mm ² for copper conductor class 5							
description	4	6	8	10	16	25	35	50
D25-50 SV(-T/-S)-V(-K)						G9917 01 10 ADERENDHÜLSE 35-18 VPE 50 STÜCK		without sleeve
D4-50 SV(-T/-S)-V(-K)	G9917 01 10 ADERENDHÜLSE 35-18 VPE 50 STÜCK							without sleeve

D-Series connector	cross section in mm ² for copper conductor class 5					
description	16	25	35	50	70	95
D16-95 SV(-T/-S)-V(-K)	G9917 01 11 ADERENDHÜLSE 70-25 VPE 25 STÜCK					without sleeve

D-Series connector	cross section in mm ² for copper conductor class 5							
description	25	35	50	70	95	120	150	
D25-150 SV(-T/-S)-V(-K)	G9917 01 13 ADERENDHÜLSE 95-32 VPE 25 STÜCK					without sleeve		
D35-150 SV(-T/-S)-V(-K)		G9917 01 13 ADERENDHÜLSE 95-32 VPE 25 STÜCK					without sleeve	

D-Series connector	cross section in mm ² for copper conductor class 5								
description	25	35	50	70	95	120	150	185	
D25-185 SV(-T/-S)-V(-K)	G9917 01 12 ADERENDHÜLSE 70-32 VPE 25 STÜCK				G9917 01 14 ADERENDHÜLSE 120-38 VPE 25 STÜCK			without sleeve	
D70-185 SV(-T/-S)-V(-K)					G9917 01 12 ADERENDHÜLSE 70-32 VPE 25 STÜCK			without sleeve	

D-Series connector	cross section in mm ² for copper conductor class 5							
description	50	70	95	120	150	185	240	
D50-240 SV(-T/-S)-V(-K)	G9917 01 03 ADERENDHÜLSE 185-56						without sleeve	
D120-240 SV(-T/-S)-V(-K)					G9917 01 03 ADERENDHÜLSE 185-56			without sleeve