

RescueMan PA System

MADE IN USA



Technical Specifications

RescueMAN Personal PA System was designed for first responders requiring voice amplification for emergencies or crowd control situations. 100 dB of crystal clear sound pumped out of a lightweight, wearable enclosure designed to be heard over loud emergency equipment or in an active environment. It also features a high quality record & replay function which allows a user to record a voice message up to 20 seconds with repeating capability.

RESCUEMAN CONTROLS



RSM-7500 WITH MIC-50



HBM-50



CHARGER INPUT

CHARGER INDICATOR

POWER INDICATOR



205 Westwood Ave, Long Branch, NJ 07740
 Phone: 866-94 BOARDS (26273) / (732)-222-1511
 Fax: (732)-222-7088 | E-mail: sales@touchboards.com



PLAY BUTTON

RECORD BUTTON

SIREN BUTTON

MICROPHONE INPUT

Model Shown: RSM-7500

RESCUEMAN MODELS

- RSM-7500** RescueMAN with shoulder strap - no holster (mic and batteries not included)
- RSM-7500H** RescueMAN with holster strap (mic and batteries not included)

ACCESSORIES

- MIC-50** Handhel microphone 1/4" plug
- HBM** Headband microphone 1/4" plug
- RC-30** Battery charging kit
- RC-RSM** Car charger
- MT-RSM** Mounting magnet

TECHNICAL SPECIFICATIONS

Rated Power Output	30 watts
Max SPL @ Rated Power	100 dB @ 1 meter
Frequency Response	100 Hz - 15 KHz +/- 3dB
Speaker Type	4 inch neodymium
Battery Type	10 'AA' alkaline
Dimensions (HWD)	6.75" x 4.6" x 3.4" (17.1 x 11.7 x 8.6 cm)
Weight	2.15 lbs / .975 Kg

Inputs	
Microphone	Lo-Z, 1/4" phone
RC-30 - Recharge Kit (optional)	
Battery Type	10 'AA' size, NiMH 2.5 AH
Charger	AC-30
AC-30 Input	120 VAC, 60Hz, 24 watts max
AC-30/220 Input	220 VAC, 50Hz, 10 watts max



(Features & Specifications Subject to Change Without Notice)