

ACCESSORIES








SETUP



AC-WRLS-MIC

Professional





TO USE

- Digital UHF Operates in the 900 MHz Band-Away from TV, Radio, and Wi-Fi Interference
- Auto Pairing- Change Frequencies Instantly
- Lavalier Microphone (3.5mm TS) with Bodypack Transmitter and Compact Receiver with 1/4" TS Output
- Built-in Li-Ion Rechargeable Batteries with up to 6 hours of use and Micro USB to USB Charging Cable
- Includes both 1/4" to 3.5mm TRS Adapter for Camera Mic Input and 1/4" to 3.5mm TRRS Adapter for Phone Mic Input
- Transmitter: Battery, Signal Strength, and Frequency Indicators Receiver: RF, AF, Lower Power and Charge LED Indicators



SPECIFICATIONS

Microphone Response: 75Hz - 18kHz

Signal to Noise Ratio: >98dB Up to 50m Working Range:

Power Supply: Li-Ion Battery **Battery Life:** Up to 6 hrs **Recharge Time:** About 1 hr

Transmission: Digital UHF (900 MHz)

902.1 - 927.6 MHz Frequencies: Volume: Adjustable Dial

Specifications subject to change without notice

