

# Body-Pack RF Receiver UR-96BP



Body-Pack radio frequency Receiver with 96 selectable channels

## Specifications

Operating Frequency Band	640–664 MHz
Selectable Channels	96 Pre-Programmed
Maximum Deviation	80 kHz, with Level Limiting
Dynamic Range	> 80 dB
THD	< 1%
Pre/De-emphasis	< 50 $\mu$ s
Audio Outputs	Aux Out, 3.5 mm 3.5 mm Ear Phone Jack
AF Control	Hi/Mid/Low Aux Out Switch
Battery	1.2 v NiMH rechargeable x2 or 1.5 v Alkaline x2
Operating Life (full charge)	14 hrs. (NiMH) or 17 hrs. (Alkaline)
Housing	Aluminum
Dimensions	1" D x 2½" W x 3⅜" H
Weight (with batteries)	10.5 oz.

## Features

- 96 UHF Channel Selectable
  - Push-button Channel Select
  - LCD Readout
    - Selected Channel #
    - Frequency
    - Battery Condition
  - Aux Output 3.5mm
  - Low Battery Power Consumption
  - Durable Metal Case
  - Hi/Mid/Low Aux Out Sensitivity Switch
  - Ear Phone Volume Control
  - Metal Belt Clip
  - Drop-In Charger Compatible
  - Requires two "AA" batteries
- Optional**
- Rechargeable Batteries, "NiMH" Duracell
  - Drop-In Charger
    - BRC-70 for Handheld or Bodypack
    - BRC-75 Dual Bodypack