

## RC Command List

**IR command table**

| Key Name | Format | Data code |
|----------|--------|-----------|
| POWER    | SANYO  | 17        |
| INPUT    | SANYO  | 40        |
| VGA      | SANYO  | 1B        |
| VIDEO    | SANYO  | 25        |
| HDMI     | SANYO  | 1F        |
| AUTO     | SANYO  | 0F        |
| MENU     | SANYO  | 00        |
| UP       | SANYO  | 18        |
| DOWN     | SANYO  | 09        |
| LEFT     | SANYO  | 19        |
| RIGHT    | SANYO  | 08        |
| OK       | SANYO  | 07        |
| KEystone | SANYO  | 03        |
| IMAGE    | SANYO  | 41        |
| FREEZE   | SANYO  | 13        |
| PATTERN  | SANYO  | 14        |
| SCREEN   | SANYO  | 1C        |
| LAMP     | SANYO  | 01        |
| MUTE     | SANYO  | 0D        |
| INFO.    | SANYO  | 02        |
| DZOOM +  | SANYO  | 1D        |
| DZOOM -  | SANYO  | 0E        |
| VOLUME + | SANYO  | 06        |
| VOLUME - | SANYO  | 23        |
| BLANK    | SANYO  | 15        |
| TIMER    | SANYO  | 42        |

| ID | Custom Code |
|----|-------------|
| 0  | 0135H       |
|    |             |
|    |             |
|    |             |
|    |             |
|    |             |
|    |             |
|    |             |
|    |             |
|    |             |
|    |             |

