



S-CIA-CM14

12-bit 4-20mA Input Adapter Sensor

Interfaces with any sensor providing a 4-20 mA signal to connect to HOBO stations compatible with smart sensors. This adapter features both a non-switched input and a battery-saving switched input that extends the life of external batteries. It also provides a trigger signal for controlling power to attached external sensors, while offering digital filtering that improves measurement accuracy with 32 readings/sample and 60 Hz noise rejection.



Key Advantages:

- 12-bit resolution
- Digital filtering improves measurement accuracy with 32 readings/sample; 4-20 mA adapter has 60 Hz noise rejection
- Measurement averaging over logging interval further enhances accuracy
- Plug-in modular connector for easy interface with HOBO stations
- Screw terminal for connecting to sensors
- HOBO RX3000 and U30 stations have room for two adapters
- Use with HOBO USB Micro Station and HOBO MicroRX Station requires Smart Sensor Consolidator Box (S-ADAPT-6) and an extension cable.
- Represents one data input channel

HOBO S-CIA-CM14 Sensor Specifications

Measurement range: 4-20 mA (measures down to 0 mA to detect error condition)

Operating temperature range: -40° to 75°C (-40° to 167°F)

Accuracy: $\pm 40 \mu\text{A} \pm 0.3\%$ of reading (over operating temperature range)

Resolution: $\pm 4.93 \mu\text{A}$

Input impedance: 124 ohms (differential input)

Sensor trigger source: Voltage: 2.5 V $\pm 2.4\%$; maximum current: 1 mA

Warm-up time: 300 ms $\pm 3\%$ (fixed)

Measurement time: 16.6 ms $\pm 3\%$ to filter out 60 Hz noise

Cable length: 14 cm (5.5 inch)

Contact Us

Sales (8am to 5pm ET, Monday through Friday)

▶ Email sales@onsetcomp.com

▶ Call 1-508-759-9500

▶ In U.S. toll free 1-800-564-4377

▶ Fax 1-508-759-9100

Technical Support (8am to 6pm ET, Monday through Friday)

▶ Contact Product Support www.onsetcomp.com/support/contact

▶ Call 1-508-759-9500

▶ In U.S. toll free 1-877-564-4377

Onset Computer Corporation

470 MacArthur Boulevard

Bourne, MA 02532