## Body-Pack RF Receiver UT-96BP









Body-Pack radio frequency transmitter with 96 selectable channels

## **Specifications**

Operating Frequency Band Selectable Channels Maximum Deviation

Dynamic Range

THD

Pre/De-emphasis

Audio Outputs

AF Control

Battery

Operating Life (full charge)

Housing

Dimensions

Weight (with batteries)

640–664 MHz

96 Pre-Programmed

80 kHz, with Level Limiting

> 80 dB < 1%

< 50 µs

Aux Out, 3.5 mm

3.5 mm Ear Phone Jack

Hi/Mid/Low Aux Out Switch 1.2 v NiMH rechargeable x2

or 1.5 v Alkaline x2

14 hrs. (NiMH)

or 17 hrs. (Alkaline)

Aluminum

1" D x 2½" W x 3¾" H

10.5 oz.

## **Features**

- 96 UHF Channel Selectable
- Push-button Channel Select
- LCD Readout
  - Selected Channel #
  - Frequency
  - Battery Condition
- Aux Output 3.5mm
- Low Battery Power Consumption
- Durable Metal Case
- Hi/Mid/Low Aux Out Sensitivity Switch
- Metal Belt Clip
- Drop-In Charger Compatible
- Requires two "AA" batteries

## **Optional**

- Rechargeable Batteries, "NiMH" Duracell
- Drop-In Charger



205 Westwood Ave, Long Branch, NJ 07740 Phone: 866-94 BOARDS (26273) / (732)-222-1511 Fax: (732)-222-7088 | E-mail: sales@touchboards.com



