

TINKER & RASOR



MODEL CI-50

50 AMPS

Current Interrupter

Features:

- Interrupt AC or DC
- ON / OFF 0.1sec to 99.9sec
- Cable with locking connector
- LEDs show OPEN / CLOSED
- View Program shows cycle settings
- Battery operated (AA batteries)
- Easy to operate / program
- Cable storage in case
- Tan colored lockable case blends in to surroundings.



AVAILABLE FROM STOCK!

Distributed by



www.teststations.com

www.tinker-rasor.com

www.detectron.com

Info@tinker-rasor.com



Tinker & Rasor quality is found in our products,
our people and our customer service.



TINKER & RASOR

CORROSION MITIGATION INSTRUMENTATION



PRODUCT DATA SHEET

MODEL CI-50 CURRENT INTERRUPTER

Features:

- Interrupt AC or DC side of the rectifier
- No polarity concerns
- 0.1s - 99.9s programming (0.1sec increments)
- Highly Accurate Internal Clock
- LEDs show OPEN and CLOSED condition during operation
- Battery operated (AA)
- Battery life up to 100 hours
- Low battery indication

Construction:

- Solid state circuitry, no mercury relays
- Hard plastic resin case with strong lid latches
- Lock case with lid locked or able to open
- Low profile tan color
- Case includes internal storage area
- Easy to read, high contrast panel

Applications:

- Interruption of CP rectifiers
- DCVG
- Pipe to Soil Potential
- Instant OFF
- Other potential readings

Specifications:

- 50 Amp max, AC or DC
- 120 Volt max, AC or DC
- (4) "AA" Batteries
- Starts in Open condition
- 19°C to 60°C (-2°F to 140°F)

Dimensions:

- 5.75" x 12.25" x 10", 5 lbs
- (146mm x 311mm x 254mm, 2.27 kg)

Shipping Dimensions:

- 14" x 12" x 6", 6 lbs

DELIVERY: **Immediately from STOCK**
F.O.B. San Bernardino, CA USA

SERVICE: **24-hour Turn-Around**

TERMS: Net 30 Days, on approval of credit

WARRANTY: **90 Days**, parts and labor



Easy to use and operate, the CI-50 can be programmed in seconds and interrupting immediately.



The small panel size of the CI-50 allows for a large amount of storage room inside the case.

The case can also be locked.



The CI-50 uses AA batteries. Easy to find and easy to replace. The AA batteries in the CI-50 will keep it operating for more than 80 hours.



The CI-50 Interrupter comes with the cable included. The single, locking connector leads to a pair of booted clamps. Cable length is 6' (1.8m) (p/n: 026-085)

AVAILABLE FROM STOCK