

CBF200 3-in-1 Circuit Breaker Finder

Circuit Breaker Finder, GFCI Receptacle Tester and Non-Contact Voltage (NCV) Detector

Features:

- Safely identify and label breaker locations within any electrical panel without removing power
- Comparison mode helps to identify the correct breaker with the signal strengths are very close
- Detect faulty wiring in 3-wire receptacles
- Lights display 6 wiring faults:
Open Ground, Open Neutral, Hot/Ground Reverse, Open Hot, Hot/Neutral Reverse, Hot on Neutral with Hot Open
- Test GFCI for proper operation
- Built-in Non-Contact Voltage Detector (80-300V, CAT III-300V)
- One person operation
- Includes Transmitter, Receiver and 9V Battery
- cETLus listed



Applications:

- Useful, one person operation tool for residential and commercial electricians, home inspectors, kitchen and bath installers, apartment/condo property managers, DIY'ers and handymen

Specifications

| Transmitter | |
|-------------------------------|---|
| Voltage | 120VAC Single Phase Two Wires (Live, Neutral) with Ground |
| Frequency | 47 ~ 63 Hz |
| GFCI Leakage Current | 7mA @ 120VAC |
| Safety Standard | CAT II 300V |
| Receiver | |
| Battery | 9V Alkaline x 1 |
| Auto Shut Down | After 10 minutes without any operation |
| Non-Contact Voltage Detection | 24-300VAC |
| Safety Standard | CAT III 300V |
| Transmitter Dimensions | 4.7 x 2.5 x 1.3" (118.5 x 63 x 32mm) |
| Receiver Dimensions | 5.1 x 2.4 x 1.5" (130 x 62 x 36.9mm) |
| Weight | 9.8oz (260g) |



Ordering Information:

CBF200 3-in-1 Circuit Breaker Finder

