

VF2
VF AC Voltage Detector

- **Non-contact detection of AC voltage**
- **Automatic audible warning buzzer**
- **Bright red voltage indicator in tip**
- **Suitable for detecting voltage at socket outlets or against wire insulation**
- **CAT III 1000 V**

DESCRIPTION

The Megger VF2 Voltage detector is a compact pen-style instrument used to identify the presence of live AC voltages from 100 V to 600 V at 50 or 60 Hz. Voltage is capacitively detected, signalled on the VF2 by an audible warning device actuated simultaneously to the red LED.

The VF2 incorporates a flashlight torch. Extended battery life is achieved by the use of a bright-white LED.

APPLICATIONS

The VF2 is used to identify the presence of AC voltage at socket outlets, switches, circuit breakers, fuses, wires and cables. It can identify breaks in conductors by tracing along the cable from the source to the point where the indicator no longer illuminates. It can also identify a blown fuse while in circuit.

SPECIFICATIONS

Voltage range: 100 V to 600 V AC 50/60 Hz

Operating Temperature: 14°F to 122°F (-10°C to +50°C)

Humidity: 32°F to 86°F (0 to 30°C) 95% Rh
86°F to 104°F (30°C to 40°C) 75% Rh
104°F to 122°F (40°C to 50°C) 45% Rh

Safety rating: IEC/EN61010-1:2001-02 over voltage Cat III 1000 V

EMC: IEC/EN 61326:1998

Battery: 2 x AAA (IEC LR03) included

Battery Life

Standby: >1 year
Flashlight: 50 hours
Volt Indicator: 50 hours (continuous)

Dimensions: 7 in. x 0.8 in. (176 mm x 26 mm)

Weight (including batteries): 1.7 oz (48 g)

ORDERING INFORMATION

Item (Qty)	Cat. No.
VF2 AC Voltage Detector	1000-213
(Only available in a box of 10, not as individual instruments)	