



MODEL		NC-X900
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, Ubuntu 18.04 and above, iOS 11.0 and above, Android 5.0 and above
		Screen Mirroring for iOS and Android
		Windows 10 Miracast
	Split Screen	Up to 4, in dynamic layout
	Mirroring Resolution	Up to 4K-UHD, 30 fps
	Output Resolution	4K-UHD (3840 x 2160), 1080p (1920 x 1080), 720p (1280 x 720)
FEATURES	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard
	Productivity	Meeting ID, QR Code connection support, PIN connection function
	Digital Signage Annocement Board	NovoDS Digital Signage - Message and Annocement Board, intuitive drag-and-drop interface, flexible playlist creation, dynamic content from text, audio, photos and videos to webpages, Twitter, RSS, Google Calendar, Weather, and more.
	Wireless Screen Duplication	NT Live Sender and Reciever for wireless screen duplication
	Security	Dual network WiFi & LAN, AES-256 encryption, Kensington lock
CONNECTIVITY	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz, 2T2R with 2 external antenna Dual WiFi modules (one dedicated for Miracast)
	Output	HDMI-Out Audio-Out (3.5mm jack)
	Input	Ethernet RJ45 (PoE); USB Type A x 1 USB Type C x 1; microSD Slot; HDMI-In; Line-In 3.5mm mini jack; RS-232 jack DC Jack Power-In
SYSTEM	CPU	Six-core ARM
	Storage	16GB
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/3A. Consumption: 15W
	Product Dimensions (L x W x H)	195.8 x 139.8 x 28 mm
	Weight (Net)	446g
	What's Included	Main Unit, 2x Antennae, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT
	Optional Accessory	LauncherPlus (USB Type A), LauncherPlus (USB Type C), LauncherOne (USB Type A)
	Warranty	2 Years



MODEL		NC-X700
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, Ubuntu 18.04 and above, iOS 11.0 and above, Android 5.0 and above
		Screen Mirroring for iOS and Android
		Windows 10 Miracast
	Split Screen	Up to 4, in dynamic layout
	Mirroring Resolution	Up to 4K-UHD, 30 fps
	Output Resolution	4K-UHD (3840 x 2160), 1080p (1920 x 1080), 720p (1280 x 720)
FEATURES	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard
	Productivity	Meeting ID, QR Code connection support, PIN connection function
	Digital Signage Annocement Board	NovoDS Digital Signage - Message and Annocement Board, intuitive drag-and-drop interface, flexible playlist creation, dynamic content from text, audio, photos and videos to webpages, Twitter, RSS, Google Calendar, Weather, and more.
	Wireless Screen Duplication	NT Live Reciever for wireless screen duplication
	Security	Dual network WiFi & LAN, AES-256 encryption, Kensington lock
CONNECTIVITY	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz 2T2R with 2 external antenna
	Output	HDMI-Out Audio-Out (3.5mm jack)
	Input	Ethernet RJ45; USB Type A x 1 USB Type C x 1; microSD Slot; RS-232 jack DC Jack Power-In
SYSTEM	CPU	Six-core ARM
	Storage	16GB
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/3A. Consumption: 15W
	Product Dimensions (L x W x H)	151 x 117 x 24.7 mm
	Weight (Net)	270 g
	What's Included	Main Unit, 2x Antennae, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT
	Optional Accessory	LauncherPlus (USB Type A), LauncherPlus (USB Type C), LauncherOne (USB Type A)
	Warranty	2 Years



MODEL		NP2000
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, Ubuntu 18.04 and above, iOS 11.0 and above, Android 5.0 and above
		Screen Mirroring for iOS and Android
		Miracast not supported
	Split Screen	Up to 4, in dynamic layout
	Mirroring Resolution	Up to 1080p, 30 fps
	Output Resolution	1080p (1920 x 1080), 720p (1280 x 720)
FEATURES	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard
	Productivity	QR Code connection support, PIN connection function
	Digital Signage Announcement Board	NA
	Wireless Screen Duplication	NA
	Security	Dual network WiFi & LAN, AES-256 encryption, Kensington lock
CONNECTIVITY	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz 2T2R with 2 internal antenna
	Output	HDMI-Out
	Input	Ethernet RJ45; USB Type A; microSD Slot; microUSB Power-In
SYSTEM	CPU	Quad-core ARM
	Storage	8GB
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/2A. Consumption: 10W
	Product Dimensions (L x W x H)	120 x 75 x 16 mm
	Weight (Net)	128 g
	What's Included	Main Unit, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT
	Optional Accessory	LauncherPlus (USB Type A), LauncherPlus (USB Type C), LauncherOne (USB Type A)
	Warranty	2 Years



MODEL		NC-X300
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, Ubuntu 18.04 and above, iOS 11.0 and above, Android 5.0 and above
		Screen Mirroring for iOS and Android
		Miracast not supported
	Split Screen	Up to 2, side by side
	Mirroring Resolution	Up to 1080p, 30 fps
	Output Resolution	1080p (1920 x 1080), 720p (1280 x 720)
FEATURES	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard
	Productivity	QR Code connection support, PIN connection function
	Digital Signage Announcement Board	NA
	Wireless Screen Duplication	NA
	Security	Dual network WiFi & LAN, AES-256 encryption, Kensington lock
CONNECTIVITY	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz 1T1R with 1 external antenna
	Output	HDMI-Out Audio-Out (3.5mm jack)
	Input	USB Type A; microSD Slot; DC Jack Power-In
SYSTEM	CPU	Quad-core ARM
	Storage	8GB
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/2A. Consumption: 10W
	Product Dimensions (L x W x H)	100 x 100 x 20 mm
	Weight (Net)	184 g
	What's Included	Main Unit, Antenna, HDMI Cable, USB Cable, Power Adapter, USB to Ethernet Adapter, Wall Mount KIT, Document KIT, QL300 LauncherPlus
	Optional Accessory	LauncherPlus (USB Type A), LauncherPlus (USB Type C), LauncherOne (USB Type A)
	Warranty	2 Years

# NovoEnterprise

## NE3000EU



<b>Model</b>	NE3000EU
<b>Support Operating System</b>	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, iOS 7.0 and above, Android 4.0 and above
<b>Desktop Streaming</b>	up to 1080p, 60 fps
<b>Screen Mirroring</b>	Google cast for Android, AirPlay for iOS
<b>Usage mode</b>	Corporate mode; Education mode
<b>Max. Participants</b>	Up to 64
<b>Split Screen</b>	Up to 4
<b>WiFi</b>	802.11ac, b/g/n, 2.4GHz & 5GHz, 2T2R with external antenna
<b>Output</b>	HDMI-Out; Audio-Out 3.5mm mini jack
<b>Output resolution</b>	FullHD1080p (1920 x 1080); WXGA (1280 x 800); HD720p (1280 x 720); XGA (1024 x 768)
<b>Input</b>	Ethernet RJ45 (PoE); USB Type A x 2; MicroSD Slot; HDMI-In; Audio-In 3.5mm mini jack; DC Jack Power-In
<b>CPU</b>	ARM Cortex A9 Quad-Core at 1.6 GHz
<b>Storage</b>	8GB
<b>Security</b>	Dual Network, AES-256 encryption, Kensington lock
<b>Power</b>	Input to AC adaptor: AC 100-240V, 50/60Hz. Output from AC adaptor: 5V/2A, Consumption: 10W
<b>Dimensions (L x W x H)</b>	165 x 123 x 21 mm
<b>Weight</b>	250 g

MODEL		NC-X300	NP2000	NC-X700	NC-X900
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, Ubuntu 18.04 and above, iOS 11.0 and above, Android 5.0 and above			
		Screen Mirroring for iOS and Android			
		Miracast not supported		Windows 10 Miracast	
	Split Screen	Up to 2, side by side		Up to 4, in dynamic layout	
	Mirroring Resolution	Up to 1080p, 30 fps		Up to 4K-UHD, 30 fps	
Output Resolution	1080p (1920 x 1080), 720p (1280 x 720)		4K-UHD (3840 x 2160), 1080p (1920 x 1080), 720p (1280 x 720)		
FEATURES	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard			
	Productivity	QR Code connection support, PIN connection function		Meeting ID, QR Code connection support, PIN connection function	
	Digital Signage Announcement Board	NA		NovoDS Digital Signage - Message and Announcement Board, intuitive drag-and-drop interface, flexible playlist creation, dynamic content from text, audio, photos and videos to webpages, Twitter, RSS, Google Calendar, Weather, and more.	
	Wireless Screen Duplication	NA		NT Live Receiver for wireless screen duplication	NT Live Sender and Receiver for wireless screen duplication
	Security	Dual network WiFi & LAN, AES-256 encryption, Kensington lock			
CONNECTIVITY	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz 1T1R with 1 external antenna	802.11ac, b/g/n, 2.4GHz & 5GHz 2T2R with 2 internal antenna	802.11ac, b/g/n, 2.4GHz & 5GHz 2T2R with 2 external antenna	802.11ac, b/g/n, 2.4GHz & 5GHz, 2T2R with 2 external antenna Dual WiFi modules (one dedicated for Miracast)
	Output	HDMI-Out Audio-Out (3.5mm jack)	HDMI-Out	HDMI-Out Audio-Out (3.5mm jack)	
	Input	USB Type A; microSD Slot; DC Jack Power-In	Ethernet RJ45; USB Type A; microSD Slot; microUSB Power-In	Ethernet RJ45; USB Type A x 1; USB Type C x 1; microSD Slot; RS-232 jack; DC Jack Power-In	Ethernet RJ45 (PoE); USB Type A x 1; USB Type C x 1; microSD Slot; HDMI-In; Line-In 3.5mm mini jack; RS-232 jack; DC Jack Power-In
SYSTEM	CPU	Quad-core ARM		Six-core ARM	
	Storage	8GB		16GB	
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/2A. Consumption: 10W		Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/3A. Consumption: 15W	
	Product Dimensions (L x W x H)	100 x 100 x 20 mm	120 x 75 x 16 mm	151 x 117 x 24.7 mm	195.8 x 139.8 x 28 mm
	Weight (Net)	184 g	128 g	270 g	446g
	What's Included	Main Unit, Antenna, HDMI Cable, USB Cable, Power Adapter, USB to Ethernet Adapter, Wall Mount KIT, Document KIT, QL300 LauncherPlus	Main Unit, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT	Main Unit, 2x Antennae, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT	Main Unit, 2x Antennae, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT
	Optional Accessory	LauncherPlus (USB Type A), LauncherPlus (USB Type C), LauncherOne (USB Type A)			
	Warranty	2 Years	2 Years	2 Years	2 Years

MODEL		NovoCast NC1000	NovoPro NP2000
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, iOS 11.0 and above, Android 5.0 and above	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, Ubuntu 18.04 and above, iOS 11.0 and above, Android 5.0 and above
		Screen Mirroring for iOS and Android	
		Miracast not supported	
	Split Screen	Up to 2, side by side	Up to 4, in dynamic layout
	Mirroring Resolution	Up to 1080p, 30 fps	
	Output Resolution	1080p (1920 x 1080), 720p (1280 x 720)	
FEATURES	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard	
	Productivity	QR Code connection support, PIN connection function	
	Digital Signage Announcement Board	NA	
	Wireless Screen Duplication	NA	
	Security	Dual network WiFi & LAN, AES-256 encryption, Kensington lock	
CONNECTIVITY	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz 1T1R with 1 external antenna	802.11ac, b/g/n, 2.4GHz & 5GHz 2T2R with 2 internal antenna
	Output	HDMI-Out Audio-Out (3.5mm jack)	HDMI-Out
	Input	USB Type A; microSD Slot; DC Jack Power-In	Ethernet RJ45; USB Type A; microSD Slot; microUSB Power-In
SYSTEM	CPU	Quad-core ARM	
	Storage	8GB	
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/2A. Consumption: 10W	
	Product Dimensions (L x W x H)	100 x 100 x 20 mm	120 x 75 x 16 mm
	Weight (Net)	184 g	128 g
	What's Included	Main Unit, Antenna, HDMI Cable, USB Cable, Power Adapter, USB to Ethernet Adapter, Wall Mount KIT, Document KIT, QL300 LauncherPlus	Main Unit, HDMI Cable, USB Cable, Power Adapter, Remote Control with Batteries, Wall Mount KIT, Document KIT
	Optional Accessory	NA	LauncherPlus (USB Type A), LauncherPlus (USB Type C), LauncherOne (USB Type A)
	Warranty	2 Years	