# **Weller**

## **WX2020**

2-Channel Soldering Station, 200 W (255 W)

Product no.: WX2020N





#### **Benefits**

- > High Powered Digital Soldering Stations WX 2
- > Capacitive glass touch screen is chemical and temperature resistant
- > Turn and click wheel with enter key and finger guide is intuitive to use
- > Multi-language menu , ready for automation using RS232 Serial I/O commands
- > Large graphic LCD display can be viewed from all angles
- Acts as a benchtop controller for the WHP1000 / WHP3000 hot plates
- > Acts as a benchtop controller for the Zero Smog 4V / 6V Filtration units
- Multi-purpose USB port for parameter configuration and DATA LOGGING
- > Compatible with all WX series soldering pencils
- > Compatible with WXMT-MS desoldering tweezers

#### For this purpose, we recommend:



Solder fume extractors



Soldering irons



Cleaning



Pre-heating plates



| Dimensions L x W x H (mm)              | 174 x 154 x 135                          |
|--|--|
| Dimensions L x W x H (inches)          | 6,85 x 6,06 x 5,31                       |
| Weight (approx.) in kg                 | 3.45                                     |
| Voltage                                | 120 V                                    |
| Power                                  | 200 W (255 W)                            |
| Channels                               | 2  |
| Temperature range (depends on tool) °C | 100 - 550                                |
| Temperature range (depends on tool) °F | 200 - 999                                |
| Temperature accuracy °C                | ±9                                       |
| Temperature accuracy °F                | ±17                                      |
| Temperature stability °C               | ±2                                       |
| Temperature stability °F               | ±4                                       |
| Equipotential bonding socket           | Via 3,5 mm pawl socket on back of device |
| Display                                | 255 x 128 dots / Backlighting            |
| Air consumption l/min                  |  |
| Operating pressure in bar/psi          |  |
| Capacity l/min                         |  |
| Vacuum                                 |  |
|  |  |

### Owning the bench









XCELITE

Phone: +49 (0) 7143 / 580-0 Fax.: +49 (0) 7143 / 580-108 Email: info@weller-tools.com Web: www.weller-tools.com