

CHG 408

Charging Bay

Charging bay for WaveCAST Receivers and Digi-Wave DLT 400 and DLR 400 RCH.



CHG 408

Dimensions:	8.3"L x 5.5"W x 1.2"H (210 mm x 140 mm x 29.5 mm)
Weight:	0.90 lbs (0.4 kg)
Color:	Black and dark transparent plastic dividers
Power Input:	18-20V DC
Power Output:	5V DC/1A for black USB ports, 5V DC/2.4A for red USB ports
Unit Capacity:	8 Units
Indicators:	One LED for indicating power to charger; no individual indicators.
Compatible Units:	CHG 408 WF: WF R1 CHG 408 DW: DLT 400, DLR 400 RCH (Appropriate USB cables can be used with any CHG 408. See Note.)
Warranty:	1 year (90 day warranty on cables and power supply)
Approvals:	WEEE, RoHS, CE, FCC
Note:	Accepts USB type A plugs, with a USB-C or with a micro-B plug that can connect to the device to be charged.

Architecture and Engineering Specifications

- The charger shall be a 8-bay, drop-in charger for use with the WF R1, DLT 400, and DLR 400 RCH.
- The charger be enclosed in black with dark transparent plastic dividers.
- The charger shall be 8.3”L x 5.5”W x 1.2”H (210 mm x 140 mm x 29.5 mm) and weigh 0.9 lbs (0.4 kg), excluding power supply.
- The charger shall be powered by an external power supply (18-20V DC input; 5V DC/1A for black USB ports, 5V DC/2.4A for red USB ports output) via a DC barrel connector.
- The charger shall have CE approval and be RoHS, WEEE, and FCC compliant.
- This charger shall be the Williams Sound model CHG 408.

Domestic Sales

Williams AV
10300 Valley View Rd
Eden Prairie, MN 55344
Ph: 800-328-6190 / 952-943-2252
FAX: 952-943-2174
Email: info@williamsav.com
Web: www.williamsav.com

International Sales

International Sales Department
Williams AV
10300 Valley View Rd
Eden Prairie, MN 55344 USA
Phone: +1 952 943 2252
Fax: +1 952 943 2174
Email: info@williamsav.com
Web: www.williamsav.com



info@williamsav.com / www.williamsav.com
800-843-3544 / INTL: +1-952-943-2252