

Brief Product Description

This digital timer is part of the BG circuit protection range of control devices and is suitable for use within any BG consumer unit or enclosure.

With 2 channel, 7 day time control with 1 minute switching and up to 58 memory inputs.

Features

- 2 Channel
- LCD Display
- Manual Override
- Daily Programme
- Simple Summer/Winter Time Correction
- 2 Module
- Accurate Time Setting

Part Code

Cat No.	Description
CUTS11	Digital Timer 2 Channel

Technical Specifications


Channels	2 Channel
Programme Type	Daily Programme
Shortest Switching Time	1 Minute
Permanent ON/Off Switch	Yes
Manual Switching	Yes
Switching Display Status	Yes
Rated Operational Voltage Ue	230V
Operating Temperature Range	-10°C - + 50°C
Languages	English/Spanish/French/ German/Portuguese/Italian
Power Reserve	5 Years
Time Accuracy	± 2 Sec/Day
Switching Capacity	Resistive Load 16A Inductive Load 4A
Memory Inputs	58
Number of Mechanical Operations	10,000
Standards	BS EN 60730-1 BS EN 6073-02-7



Product Images



Dimensional Line Drawing



Dimensions of Product

Height: 85.6mm
Width: 35.8mm
Depth: 74.3mm



Guarantee

BG Electrical Circuit Protection products are guaranteed against faulty materials and workmanship for a period of 10 years from date of delivery.

Products will be repaired or (at BG Electrical's discretion) replacements will be supplied or (at BG Electrical's discretion) a credit note will be issued. This guarantee is subject to BG Electrical's conditions of sale and in particular to the following conditions being met.



1. Notification of any defect is given as soon as reasonably practicable after becoming apparent, and the products then returned to BG Electrical.
2. The products have only been operated under normal operating conditions and have only been subject to normal use.
3. No work (other than normal and proper maintenance) has been carried out to the products without BG Electrical's prior written consent.
4. The products have been assembled, or incorporated into other goods, by a qualified and recognised electrician and only in accordance with any instructions issued by BG Electrical.
5. The defect has not arisen from an item manufactured or supplied by a person other than BG Electrical.

This guarantee does not affect any customer statutory rights.

All components used in a BG Electrical enclosure, must be supplied by BG Electrical.

The use of any other components will negate compliance to BS 61439 and the BG Electrical guarantee. Failure to fit the enclosure in accordance with these instructions will invalidate the guarantee.