

PRODUCT-DETAILS

9368.1

Sound device



Informations générales

Extension du type de produit	9368.1
Code de produit	2CLA936810A1001
EAN	8427238104348
Description courte	Sound device
Description longue	<p>Rated voltage: 127-230 Vac \pm 15%; 50-60 Hz Max. consumption: 200 mA Stand-by consumption: 0,3W Amplifier power: 6+6 W; <1% distortion (4 Ω) Speaker impedance: 4 Ω (2+2 W audio) FM radio digital tuner with RDS Alarm clock with buzzer, radio types and snooze function Bluetooth receiver: Bluetooth® v2.1 2.4GHz IEEE 802.15.1 Multiroom function available (1 master device and up to 14 slave devices) Remote control using code 9368.2 (ZigBee 2.4GHz IEEE 802.15.4) Optional: auxiliary module 9368.3 for I/O (1 mini-jack stereo input & 1 mini-jack stereo output) and USB connection functions</p>

Installation

Instructions et manuels	2CLX936810A1001
-------------------------	-----------------

Technique

Fiche produit, informations techniques	9AKK107046A0356
--	-----------------

Tension nominale (U _r)	230 V
Fréquence (f)	50...60 Hz
Nombre de sorties	Analog (0 ... 10 V / 4 ... 20 mA) 0
Design Range	Zenit
Nombre de batteries	0
Application Function	Data Communication / Multimedia

Environnement

Température de l'air ambiant	Operation -5 ... +35 °C Storage -5 ... +50 °C
Indice de protection	IP20
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Dimensions

Produit Largeur Net	0.047 m
Produit Hauteur Net	0.109 m
Produit Longueur Net	0.293 m
Poids net	0.078 kg

Commande

ID du produit remplacé	2CLA936810A1002
------------------------	-----------------

Certificats et Déclarations (Numéro de document)

Déclaration de Conformité - CE	9AKK107492A7831
--------------------------------	-----------------

Classifications

ETIM 8	EC002484 - Sound system for domestic switching devices
ETIM 9	EC002484 - Sound system for domestic switching devices
Catégorie DEEE	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85389099
UNSPSC	39121311

Catégories

Produits basse tension → Wiring Accessories - Light Switch Ranges → Flush Mounted Inserts → Multimedia

