



LarK-111



LarK-111 · HONEYCOMB LOUVER



reddot design award
winner 2014



| LarK-111 | | P | CCT | Beam | I | Flux | Flux Out | LOR |
|---------------|-----------------------|------|-------|------|-------|--------|----------|-----|
| PHASE CUT * | A25 Ⓞ -10-10- W N | 6,5W | 2700K | 19° | 200mA | 900Lm | 828Lm | 92% |
| | A25 Ⓞ -10-11- W N | 6,5W | 3000K | 19° | 200mA | 940Lm | 865Lm | 92% |
| | A25 Ⓞ -10-12- W N | 6,5W | 4000K | 19° | 200mA | 950Lm | 874Lm | 92% |
| | A25 Ⓞ -10-20- W N | 6,5W | 2700K | 40° | 200mA | 900Lm | 774Lm | 86% |
| | A25 Ⓞ -10-21- W N | 6,5W | 3000K | 40° | 200mA | 940Lm | 808Lm | 86% |
| PHASE CUT * | A25 Ⓞ -10-22- W N | 6,5W | 4000K | 40° | 200mA | 950Lm | 817Lm | 86% |
| | A25 Ⓞ -20-10- W N | 12W | 2700K | 19° | 350mA | 1440Lm | 1325Lm | 92% |
| | A25 Ⓞ -20-11- W N | 12W | 3000K | 19° | 350mA | 1500Lm | 1380Lm | 92% |
| | A25 Ⓞ -20-12- W N | 12W | 4000K | 19° | 350mA | 1520Lm | 1398Lm | 92% |
| | A25 Ⓞ -20-20- W N | 12W | 2700K | 40° | 350mA | 1440Lm | 1238Lm | 86% |
| PHASE CUT * | A25 Ⓞ -20-21- W N | 12W | 3000K | 40° | 350mA | 1500Lm | 1290Lm | 86% |
| | A25 Ⓞ -20-22- W N | 12W | 4000K | 40° | 350mA | 1520Lm | 1307Lm | 86% |
| | A25 Ⓞ -21-10- W N | 12W | 2700K | 19° | 350mA | 1440Lm | 1325Lm | 92% |
| | A25 Ⓞ -21-11- W N | 12W | 3000K | 19° | 350mA | 1500Lm | 1380Lm | 92% |
| | A25 Ⓞ -21-12- W N | 12W | 4000K | 19° | 350mA | 1520Lm | 1398Lm | 92% |
| DALI PUSH * | A25 Ⓞ -21-20- W N | 12W | 2700K | 40° | 350mA | 1440Lm | 1238Lm | 86% |
| | A25 Ⓞ -21-21- W N | 12W | 3000K | 40° | 350mA | 1500Lm | 1290Lm | 86% |
| | A25 Ⓞ -21-22- W N | 12W | 4000K | 40° | 350mA | 1520Lm | 1307Lm | 86% |

LED | 220-240V~ | CE | CRI>90 | L80B10 > 60.000h




Ⓞ OPTIONS


| | |
|---|----------------------|
| 2 | LarK-111 |
| 3 | LarK-111 Honeycomb** |

* OTHER DIM OPTIONS PLEASE CONSULT | ** Honeycomb affects lighting parameters

LarK-111



LarK-111 · HONEYCOMB LOUVER



COLOUR | W □ RAL 9016 | N ■ RAL 9005 | MATERIAL | AL

Bluetooth & Wi-Fi » PLEASE CONSULT

Calle N · Pol. Ind. EL OLIVERAL
46394 Ribarroja del Turia · Valencia (Spain)
Tel. +34 961 667 207 · Fax +34 961 667 054
info@arkoslight.com · www.arkoslight.com

