BT-626/FRA

04634

DESCRIPTION

Professional 6 channel Dimmer / Switch pack for 19" rack mounting

FEATURES

- Professional 6 channel Dimmer / Switch pack for 19" rack mounting
- Max load 16A (3680W) per channel with automatic 16A circuit breakers
- Suitable for both inductive and resistive loads
- Can be used to dim incandescent lamps, halogen lamps, low volt halogen lamps with ballast and dimmable LED-lamps (load must be >100W).
- Outputs equipped with French mains sockets (see barcode sticker)
- DMX (3p-XLR + RJ11) and analog 0/10V (dB9) inputs
- Block or individual channel addressing (soft patch)
- Switch/dimmer mode can be set individually for all channels
- Control faders 0-100% for all channels (no external controller needed)
- Preheat control to extend lamp life: 0-6%
- Automatic phase/frequency tracking (45Hz to 63Hz) for improved dimming under difficult conditions.
- LED display for monitoring of all functions, including internal temperature.
- Mains input (200 ~ 240Vac):
 - 3-phase/4wire: total max. load = 22kW
 - Single phase/2wire: total max. load = 9,6kW
- Intelligent thermo protection with automatic fan control.
- Dimensions: 483x88x312mm (19"/2U)
- Weight: 8kg









www.briteq-lighting.com | https://www.facebook.com/Briteq

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2015 by BEGLEC NV. All rights reserved.

SPECIFICATIONS

General: Application

DJ & Club, Stage & Rental,
Theatre

Theatre

General : Dimensions (cm) $48.3 \times 8.8 \times 31.2 \text{ cm}$

General: Weight (kg) 8.5

General: Powerinput AC 240V, 50Hz

General : Energy Label No **General : Power consumption W** -

General : Color black
General : Display LED

General : Fixation 19" rack mountable

General: RU No
General: IP rating indoor
Control: manual No
Control: Standalone automatic
Control: programmable No
Control: upgradable software No
Control: maximum DMX channels 6
Connections: input Connections: output -

Brand BRITEQ

EANCode 5420025646345

Discontinued No

YOUR DEALER



www.briteq-lighting.com | https://www.facebook.com/Briteq