

PRODUCT-DETAILS

N2192 RJ

LED kit for switch Switch/push button White LED 110...220 V - Zenit



Informations générales

Extension du type de produit	N2192 RJ
Code de produit	2CLA219200N1001
EAN	8427238063454
Description courte	LED kit for switch Switch/push button White LED 110...220 V - Zenit
Description longue	Suitable for 1-gang, 1-way, DP switches, 1-gang, 2-ways, SP and 1-gang, intermediate switches. Rated voltage: 230 Vac. Toolless front connection. Includes diffusers for 1 and 2 module rocker covers. Rated current: <0,2 mA. Specially designed for CFL and LED lamps.

Installation

Instructions et manuels	2CLX210109N1001
-------------------------	-----------------

Technique

Fiche produit, informations techniques	9AKK10103A5108
Application	Switch/push button
Tension nominale (U _r)	110...220 V
	0.2 mA

Design Range	Zenit
Type de lampe	LED
Lamp Color	White
Nombre de batteries	0

Environnement

Température de l'air ambiant	Operation -5 ... +35 °C Storage -5 ... +50 °C
Statut RoHS	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
Informations RoHS	2CLC219200N1001
Informations environnementales	9AKK108467A3734
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Dimensions

Produit Largeur Net	13 mm
Produit Hauteur Net	29 mm
Poids net	0.003 kg

Commande

ID du produit remplacé	2CLA219200N1002 2CLA219200N1003
------------------------	------------------------------------

Certificats et Déclarations (Numéro de document)

Déclaration de Conformité - CE	No declaration needed
--------------------------------	-----------------------

Classifications

ETIM 8	EC000199 - Illumination insert for domestic switching devices
ETIM 9	EC000199 - Illumination insert for domestic switching devices
Catégorie DEEE	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85414010

Catégories

Produits basse tension → Wiring Accessories - Light Switch Ranges → Accessories → Accessories Mechanics

