

SORAA MR16 12V 9W - DIMMER/MLV TRANSFORMER COMPATIBILITY - North America

NC - SORAA does not recommend this transformer for use with its lamps;

Transformer	Model	Transformer Type	Number of Lamps (Load)	Dimmer -->	Lutron Skylark SLV-600P	Lutron Diva DVLV-600P	Lutron Radio RA2 RRD-6NA	Marlin Controls Stellar	Lutron Maestro MACL-153M	Lutron Grafik Eye QSGR (3000 & 4000 systems)
Cooper	T50W120VSL	Magnetic	1		NC	25%	6%	1%	7%	5%
Cooper	TF-149911	Magnetic	1		22%	24%	5%	4%	6%	4%
Cooper	TF 149911-TP120	Magnetic	1		14%	23%	6%	4%	6%	4%
Cooper	TFA4120	Magnetic	1		21%	24%	5%	4%	7%	4%
Hatch	LS1275EN/12V	Magnetic	1		21%	22%	5%	5%	88%	4%
Juno	310-1333	Magnetic	1		21%	26%	6%	1%	65%	5%
Q-TRAN	QT10-120/12-TP-RC	Magnetic	1		21%	15%	4%	4%	6%	4%
Q-TRAN	QT20-120/12-TP-RC	Magnetic	1		21%	24%	4%	4%	6%	4%
Q-TRAN	QT50SV-120/12-RC	Magnetic	1		22%	25%	5%	1%	6%	5%

Notes:

Compatibility tests are conducted by Soraa under bench conditions as guidance for the user; results at the application site may differ due to variability in usage conditions or in dimmer or transformer components/manufacturing.

If the transformer's minimum wattage is not met, the lamp may only operate under nominal conditions (nominal line voltage and thermal conditions where the lamp is at full power). Transformer maximum load listed in the transformer compatibility table should not be exceeded.

If the dimmer and transformer is not listed, please consult with Soraa before making recommendations to the end customer.

	Dims to < 20%
NC	Not compatible
	Not tested