

SORAA MR16 12V 7.5 & 9W - 120V ELV DIMMER/TRANSFORMER COMPATIBILITY - North America

NC - SORAA does not recommend this transformer for use with its lamps;

120V PHASE-DIMMABLE ELV TRANSFORMERS WITH REVERSE PHASE DIMMERS														
Transformer (120V)	Model	Transformer Type	Number of Lamps (Load)	Dimmer -->	CRESTRON DIN-1DIMU4	Lutron Diva DVELV-300P	Lutron Skylark SELV-300P	Lutron Radio RAZ RRD-6NA- WH 600W ///// HomeWorks HQRA-6NA	Lutron LCP 120V	Lutron Grafik Eye OS +PHPM	Lutron Spacer SPSELV-600	Lutron Maestro MAELV-600	Lutron Nova T NTELV-300	Marlin Stellar DIMMING CABINET P/N 6-3-08-20-3- 103T
B+L	FX95100	Electronic	1		8%	7%	7%	4%	7%	3%	13%	NC	12%	4%
Hatch	RS1215BFLED	Electronic	1		8%	8%	9%	4%	NC	3%	8%	17%	9%	2%
Hatch	RS12-60M	Electronic	2		8%	8%	9%	5%	5%	3%	8%	21%	8%	2%
Hatch	RL12-75A	Electronic	2		NC	6%	7%	5%	NC	4%	NC	NC	9%	4%
Hatch	RS12-150	Electronic	3		8%	8%	9%	4%	3%	5%	9%	19%	9%	4%
Hatch	RS12-15M-LED	Electronic	1			7%		8%						
Hatch	RS12-30M-LED	Electronic	2				9%					9%		
Hatch	RS12-60M-LED	Electronic	1		8%	8%	9%	4%	NC	4%	8%	17%	8%	3%
Juno	T537QJU	Electronic	1		8%	8%	9%	4%	NC	4%	8%	17%	8%	3%
Juno	T537U	Electronic	1		8%	8%	9%	4%	NC	4%	8%	17%	8%	3%
Lightech	LET60	Electronic	1		8%	9%	6%	5%	NC	3%	8%	14%	10%	4%
Lightech	LET60-LW	Electronic	1		8%	8%	9%	4%	5%	3%	8%	21%	21%	4%
Lightech	LET75	Electronic	1		NC	6%	4%	3%	NC	8%	8%	16%	16%	2%
LTF	TA60WA12LED	Electronic	1		8%	8%	8%	2%	5%	2%	8%	17%	17%	4%
LTF	TA105WA12LED-0000	Electronic	3		5%	9%	8%	3%	5%	3%	8%	17%	9%	4%
LTF	TA300WDS12LEDRE	Electronic	3		8%	9%	9%	5%	6%	5%	8%	NC	9%	3%
WAC	EN1260	Electronic	1		8%	8%	9%	3%	NC	2%	8%	20%	20%	3%

SORAA MR16 12V 7.5 & 9W - 120V ELV DIMMER/TRANSFORMER COMPATIBILITY - North America

NC - SORAA does not recommend this transformer for use with its lamps;

120V NON PHASE-DIMMABLE TRANSFORMERS WITH DIFFERENT CONTROLS						
Transformer	Model		Number of Lamps (Load)	Controllers, Potentiometers, PWM dimmers -->	Potentiometer	0-10V
NA						
Fulham	T1M1UNV012V-20L (120V & 277V)	Electronic/DC	1		0%	0%
Meanwell	PWM-90-12 (120V & 277V)	Electronic/DC	1		0%	0%
Meanwell	PWM-120-12 (120V & 277V)	Electronic/DC	1		0%	0%

Notes:

Compatibility tests are conducted by Soraa (unless stated otherwise) under bench conditions as guidance for the user.

Regards compatibility tests conducted by dimmer / transformer manufacturer, please contact Soraa or the manufacturer for more details and/or reports.

Results at the application site may differ due to variability in usage conditions or in dimmer or transformer components/manufacturing.

If the transformer's minimum wattage is not met, the lamp may only operate under nominal conditions (nominal line voltage and thermal conditions where the lamp is at full power).

Transformer maximum load listed in the transformer compatibility table should not be exceeded.

If the dimmer and/or transformer is not listed, please consult with Soraa before making recommendations to the end customer.

(*) One or more test results with this transformer added to the compatibility list as of Revision D

--%	Dims to < 20% (of the measured light output)
--%	Dims to 20-30% (of the measured light output)
NC	Not compatible (or dims to >30%)
Blank cell	Not tested