



2023 Baseline Wattages

Fixture	T8 Lamps					
	F17 17W (2 ft.)	F25 25W (3 ft.)	F32 25W (4 ft.)	F32 28W (4 ft.)	F32 32W (4 ft.)	FU32 32W (U-bend)
1 lamp	18	26	24	26	31	32
2 lamps	33	46	44	49	58	60
3 lamps	47	68	66	75	85	—
4 lamps	59	88	85	99	112	—

Fixture	T12 Lamps			
	F20 20W (2 ft.)	F40 34W (4 ft.)	F96 60W (8 ft.)	FU40 40W (U-bend)
1 lamp	25	43	75	43
2 lamps	50	72	123	72
3 lamps	71	115	210	—
4 lamps	100	144	246	—

Fixture	T5 Lamps		
	F14 14W (2 ft.)	F28 28W (4 ft.)	F54 54W (4 ft.) HO
1 lamp	18	33	62
2 lamps	33	63	117
3 lamps	50	96	179
4 lamps	66	126	243

HID	
50W	66
70W	89
75W	93
100W	110
150W	178
175W	210
200W	237
250W	290
310W	354
320W	365
350W	383
360W	416
400W	455
450W	486
700W	780
750W	814
1,000W	1,080
1,500W	1,608

Default Wattage Notes:

For Quartz-Halogen bulb retrofits, the default wattage is the nominal wattage listed on the bulb.

If you have an existing fixture that is not listed on this chart, please contact your local energy advisor for more information.