

Eaton A200MACAC

Catalog Number: A200MACAC

Eaton Freedom NEMA motor control starter, Non-Reversing Starter, 120V/60 Hz or 110V/50 Hz coil voltage, 9A, Three-pole, 1/3 hp at 115V, 1-1/2 hp at 208,240V, 2 hp at 480,600V, A200 series, Wired for Separate Control

General specifications

Product Name	Catalog Number
Eaton A200 NEMA motor control	A200MACAC
UPC	Product Length/Depth
786678231051	4.61 in
Product Height	Product Width
3.31 in	4.38 in
Product Weight	Warranty
2.6 lb	Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.
Certifications	Catalog Notes
UL Listed CSA Certified	For ambient compensated overload relay with auto-reset, add Suffix D.



Product specifications

Accessories

Motor control

Size

0

Series

A200

Coil voltage

110-120 Vac, 50/60 Hz

Phase

Three-phase magnetic

HP rating - max

1/3 hp at 115V, 1-1/2 hp at 208,240V, 2 hp at 480,600V

Amperage rating

9A

Resources

Catalogs

[Eaton's Volume 5—Motor Control and Protection](#)

Installation instructions

[Instructions for A200, A210, A250 size 6, two- or three-pole non-reversing or reversing motor controllers](#)

Specifications and datasheets

[Eaton Specification Sheet - A200MACAC](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)