

Specifications



Photo is representative

Eaton AN16BN0EC

Eaton Freedom NEMA motor control starter, Non-Reversing Reset Overload Relay Starter, 1 hp at 115V, 2 hp at 230V, 3 hp at 208,240V, 5 hp at 480,600V maximum horsepower, 208V/60 Hz coil voltage, 18A, Three-pole, Size 0

General specifications

PRODUCT NAME	Eaton Freedom NEMA motor control starter
CATALOG NUMBER	AN16BN0EC
UPC	782113025353
PRODUCT LENGTH/DEPTH	6 in
PRODUCT HEIGHT	3.4 in
PRODUCT WIDTH	1.9 in
PRODUCT WEIGHT	2 lb
WARRANTY	Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.
CERTIFICATIONS	CSA Certified UL Listed
CATALOG NOTES	Heater Packs must be purchased separately

Product specifications

SPECIAL FEATURES	Starter w/C306 bi-metal OLR
HP RATING - MAX	1 hp at 115V, 2 hp at 230V, 3 hp at 208,240V, 5 hp at 480,600V
PHASE	Single-phase, three-phase
AMPERAGE RATING	18A
SIZE	0
MOUNTING	Horizontal

Resources

CATALOGS	Motor Control and Protection, NEMA Contactors and Starters, Volume 5, Tab 2
SPECIFICATIONS AND DATASHEETS	Eaton Specification Sheet - AN16BN0EC

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc

Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

