



Transformers

AUTO-TRANSFORMER AUTOXFMR 480:277 350VA C&C

Stepdown transformers and autotransformers are used when you need to connect a lower voltage device to a higher voltage source.

Product data


General Information					
Circuit Type	Transformer				
Ballast Type	Magnetic HID				
Base Model	71A9843				
Core Size	7/8" E/I				
Suitable For Outdoor Use	Yes				
Operating and Electrical					
Input Voltage	347:190 or 480:270 V				
Input Frequency	60 Hz				
Input Current (Nom)	1 A				
Rated Lamp Power	350 VA load W				
Wiring					
Wire Striplength	0.5 mm				
Wire Length by Color	12"				
Wire Type	Stranded				
Remote Wiring Configuration Allowed Yes					
Mechanical and Housing					
Housing	NA				

Housing Dimensions	NA					
Approval and Application						
Approval Marks	ULR CSA certificate RoHS Compliant					
Temperature Marking	NA					
UL Recognized	Yes					
UL Insulation Class	H(180°C)					
UL Temperature Code	NA					
Product Data						
Order product name	AUTO-TRANSFORMER AUTOXFMR 480:277					
	350VA C&C					
EAN/UPC - Product	781087069110					
Order code	913710663402					
Numerator - Quantity Per Pack	1					
Numerator - Packs per outer box	12					
Material Nr. (12NC)	913710663402					
Net Weight (Piece)	1.665 kg					

Datasheet, 2019, March 22 data subject to change

Transformers

Dimensional drawing



AUTO-TRANSFORMER 71A9843600

Product	C1	C2	A1	A2	B1	B2
AUTO-TRANSFORMER AUTOXFMR	3.6 in	2.35 in	2.6 in	2.2 in	2.2 in	1.8 in
480:277 350VA C&C						



© 2019 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.