



Representative Image

## Catalog No. THQL1115AF2S

**Description:** THQL 1P 120V 15A AFCI SHORT WIRE

**UPC No** 783164618228

**Home > Circuit Breakers > Residential Circuit Breakers > Arc Fault**

Arc fault breakers are designed to detect and prevent damages from arcing caused by damaged wire insulation or a frayed extension cord. All Q Line circuit breakers are one inch wide per pole, compact devices that feature: Quick-make / Quick-break mechanisms, common trip bars, and easy-to-spot trip indications to ensure safety and reliability. AF2 is called a Combination breaker as it protects against arcs in both parallel and series and meets current NEC standards. The THQL1120AQF2S breaker features arc-fault interrupting technology, a short pigtail for easy wiring, 1 pole, an ampere rating of 15 A, an interrupting rating of 10kAIC, and a voltage rating of 120/240V.

### Descriptors

|              |                  |
|--------------|------------------|
| Category     | Arc Fault        |
| Product Line | Q-Line (Plug-In) |

### Specifications

|                                 |                |
|---------------------------------|----------------|
| Interrupting Capacity Rating    | 10 kAIC        |
| Voltage                         | 120/240 V      |
| Neutral Connection              | Short Pig Tail |
| Amperage                        | 15 A           |
| System Voltage                  | 120/240 Vac    |
| Poles                           | 1              |
| Continuous Current Rated        | Standard       |
| 120/240 Vac Interrupting Rating | 10 KAIC        |
| Long Time                       | Fixed          |
| Protective Relays               | No             |

### Classifications

|           |      |
|-----------|------|
| UL File # | 1699 |
|-----------|------|