

Product information

97 33 01

KNIPEX MultiCrimp®

Lever Action Crimping Pliers with changer magazine


- Just one tool for the most common crimping applications
- Crimping dies changed quickly and easily without any additional tool
- Sorted and protected storage of the interchangeable dies in a round magazine
- Comfortable, powerful crimping pliers in professional quality
- Same reliable crimping results as with fixed crimping dies
- Consistently high crimping quality thanks to precision dies and forced locking mechanism (unlockable)
- Chrome vanadium electric steel in special quality, oil-hardened
- Round magazine: plastic, fibreglass-reinforced




General

| | |
|-----------------|----------------------------|
| Article No. | 97 33 01 |
| EAN | 4003773066927 |
| Pliers | burnished |
| Handles | with multi-component grips |
| Weight | 770 g |
| Dimensions | 250 x 75 x 28 mm |
| REACH compliant | yes |
| RohS compliant | no |


Technical details



| | |
|--------------------------------|---|
| Applications | non-insulated open plug type connectors (plug width 4.8 + 6.3 mm) |
| Capacity in square millimetres | 0.5 — 6.0 mm ² |
| Number of crimping positions | 3 |
| AWG | 20 — 10 |



| | |
|--------------------------------|--|
| Applications | insulated terminals, plug connectors + butt connectors |
| Capacity in square millimetres | 0.5 — 6.0 mm ² |
| Number of crimping positions | 3 |
| AWG | 20 — 10 |



| | |
|--------------------------------|----------------------------|
| Applications | Wire ferrules |
| Capacity in square millimetres | 0.25 — 6.0 mm ² |
| Number of crimping positions | 5 |
| AWG | 24 — 10 |

| Classification | |
|-----------------------|---|
| eCl@ss 5.1.4 | 21040301 |
| ETIM 5.0 | EC000168 |
| ETIM 6.0 | EC000168 |
| proficl@ss 6.0 | AAA946c003 |
| UNSPSC 13.1 | 27112147 |
| Accessories | |
| 97 39 05 | Crimping die for non-insulated open plug type connectors (plug width 4.8 + 6.3 mm), |
| 97 39 09 | Crimping die for insulated and non-insulated wire ferrules, |
| 97 39 13 A | Crimping die for non-insulated crimp terminals, tube and compression cable lugs in accordance with DIN 46234 and DIN 46235 and non-insulated crimp, butt and press connectors in accordance with DIN 46341 and DIN 46267, |
| 97 39 06 | Crimping die for insulated terminals, plug connectors and butt connectors, |
| 97 39 08 | Crimping die for insulated and non-insulated wire ferrules, |
| 97 39 13 | Crimping die for non-insulated crimp terminals, tube and compression cable lugs in accordance with DIN 46234 and DIN 46235 and non-insulated crimp, butt and press connectors in accordance with DIN 46341 and DIN 46267, |
| 97 39 90 | Changer magazine empty, |

technical change and errors excepted



Changing the crimping dies: unlock the magazine position, take out the set of dies which the pliers have been pushed on



Changing position: service lever opens out for parallel jaw positioning



Fold in the service lever and press the pliers – ready for use again



