CURRENT TRANSFORMER CABINETS - GALVANIZED- CSA 1

CT cabinets are used with instrument rated meters, to meter single-phase services greater than 400 amps (320 amps continuous), and three-phase services greater than 200 amps.


Meets updated revenue meter specification March 2019

- Indoor application
- Galvanized steel
- Sealing screws
- Screw cover
- Back panel

www.codeelectric.com

- 4 internal mounting holes
- Grounding provisions
- CSA Certified Type 1
- Certified by BC Hydro
- isolated neutral option





BC Hydro Use							
CAT No:	Single Phase Service	Three Phase Service					
CT-G-301608	Up to 400 Amps						
CT-G-421816	425 Amps and above						
	425 Amps and above	up to 600 Amps					
CT-G-423624	N/A	601 - 1000 Amps					

CAT No:	Н	W	D	A (Back Panel Length)	B (Back Panel Width)	LBS. For Galvanize
CT-G-301608	30	16.5	8	23	14.5	#
CT-G-302010	30	20	10	23	17	#
CT-G-303010	30	30	10	23	27	#
CT-G-421809	42	18	9.5	36	16.5	#
CT-G-421816	42	18	16	36	16.5	#
CT-G-423624	42	36	24	36	34.5	#

Isolated Neutral Lug (If required)	АМР	Incoming Wire Range	Branch Wire Range
PAD-T-600	600	Four 1/0 - 250 MCM or Two 4 - 600 MCM	Two 14 - 3/0 Four 6 - 4/0

